


Operating Instructions for Magnetic Inductive Flowmeter Model: MIM





We don't accept warranty and liability claims neither upon this publication nor in case of improper treatment of the described products.

The document may contain technical inaccuracies and typographical errors. The content will be revised on a regular basis. These changes will be implemented in later versions. The described products can be improved and changed at any time without prior notice.

© Copyright

All rights reserved.

1. Contents

1.	Contents		2
2.			
		of the device functionality	
3.		ection	
4.			
5.			
6.		iple	
	6.2 Minimum	electrical conductivity / Gas bubbles	6
	6.3 Deposits	······································	6
		g electrodes	
7.		nection	
	7.1 Check ope	erating conditions	7
	7.2 Installation	n	7
8.	Electrical Conne	ection	9
	8.1 General		9
		nment	
		on example outputs:	
9.		menu structure	
		g mode	
		de	
10.		ation	
		e of device parameterization	
		9	
		nent	
		nction	
		ice	
		Factory service	
		efault settings	
	•		
13.		l	
	13.1 Specificat	ion	51

page 2 MIM 01/0721

14. Technical Information	52
15. Order Codes	55
16. Dimensions	57
17. Appendix	59
17.1 IO-Link process data structure	
17.2 IO-Link diagnosis information	
17.3 IO-Link system command table	61
17.4 IO Link ISDU parameter table	62
18. Manufacturer's declaration	
19. EU Declaration of Conformance	75
20. UK Declaration of Conformity	76

Manufactured and sold by:

KOBOLD Instruments Inc 1801 Parkway View Drive Pittsburgh PA 15205-1422 Tel.: 412-788-2830 Fax: 412-788-4890

E-Mail: info@koboldusa.com Internet: www.koboldusa.com

2. Note

Please read these operating instructions before unpacking and putting the unit into operation. Follow the instructions precisely as described herein.

The devices are only to be used, maintained and serviced by persons familiar with these operating instructions and in accordance with local regulations applying to Health & Safety and prevention of accidents.

When used in machines, the measuring unit should be used only when the machines fulfil the EC-machine guidelines.

as per PED 2014/68/EU

In acc. with Article 4 Paragraph (3), "Sound Engineering Practice", of the PED 2014/68/EU no CE mark.

Diagram 8, Pipe, Group 1 dangerous fluids

2.1 Overview of the device functionality



Depending on the installed device firmware, the MIM device may have different functionalities. The functional extensions are shown in the following table.

Function extension	Available from firmware version
Dosing function	REV180118
Menu languages	
Simulation function	
User function keys	REV180514
Analogue output 2-10 V _{DC}	
Analogue output behavior acc. to NAMUR NE43	
IO-Link	REV190320
Control input	REV190320
Additional flow units L/s and mL/s	REV191030
Filter function for flow and temperature	DE//200608
measurement	REV200608

The installed software version is displayed after starting the device below the manufacturer logo in the form REVxxxxxx for approx. 2 sec.

page 4 MIM 01/0721

3. Instrument Inspection

Instruments are inspected before shipping and sent out in perfect condition. Should damage to a device be visible, we recommend a thorough inspection of the delivery packaging. In case of damage, please inform your parcel service / forwarding agent immediately, since they are responsible for damages during transit.

Scope of delivery:

The standard delivery includes:

Electromagnetic Flowmeter model: MIM

Operating Instructions

4. Regulation Use

The MIM flowmeter has been specially developed for the measurement, display and transmission of both, flow rates and temperature of conductive liquids. The instrument has a graphic TFT display, rotatable in 90 ° steps and can display flow rate, temperature, daily volume counter (resettable) and total volume counter in the units of measurement selected by the operator. A clear menu guides the user through the parameterization of the device, which largely eliminates the need to look into the operating instructions.


Any use of the magnetic flowmeter, model: MIM, which exceeds the manufacturer's specification, may invalidate its warranty. Therefore, any resulting damage is not the responsibility of the manufacturer. The user assumes all risk for such usage.

5. Environment

The MIM device with stainless steel housing and stainless steel electrodes is weatherproof and conforms to protection class IP67. The meter is designed for harsh indoor or outdoor environments and complies with Directive 2014/30/EU (Electromagnetic Compatibility).

To avoid moisture in the device from condensation, a pressure compensation element is integrated on the front.

This element must not be pierced.



6. Operating principle

6.1 General

The new KOBOLD MIM Flowmeter is designed to measure and monitor small and medium flows of conductive fluids in piping.

The device works on the magnetic-inductive measuring principle. According to Faraday's law of induction, a voltage is induced in a conductor moving in a magnetic field. The electrically conductive measuring medium corresponds to the moving conductor in the process. The voltage induced by the measuring medium is proportional to the flow rate and thus a measure of the volume throughput. Prerequisite is a minimum electrical conductivity of the flowing medium. The induced voltage is fed to a measuring amplifier via two electrodes, which are in conductive contact with the medium. The volume flow is calculated via the defined pipe diameter.

The measurement is independent of the medium and its physical properties such as density, viscosity and temperature. The device can be configured via the display. There are two outputs available, which can each be configured as alarm, frequency, pulse, voltage, and current outputs.

The device also provides a dosing function. The dosing function can be activated in measuring mode via the four buttons. The dosing function controls simple filling tasks and also measures flow rate and partial amount.

6.2 Minimum electrical conductivity / Gas bubbles

For the correct function of the instrument, it is necessary that the flow channel is always completely filled with medium. From a minimum electrical conductivity of 20 μ S / cm, the MIM operates within the specified error limits. The conductivity of the medium is constantly monitored by the device electronics. If the electronics detects that the minimum conductivity has fallen below min. value, this is signaled by displaying the error message 'Empty pipe' and the flow rate reading is set to '0'. Air bubbles in the flowing medium or media with varying conductivity in the range of the minimum conductivity can disturb the measuring function and reduce the measuring accuracy of the MIM. Gases contained in the liquid are also measured as a flow volume and lead to measurement errors. If necessary, install appropriate vents in the flow of the unit.

6.3 Deposits

Minor deposits on the measuring tube generally do not affect the measuring accuracy unless their conductivity deviates significantly from the liquid. For liquids that have a tendency to deposit, periodically inspect the meter tube and, if necessary, clean it.

page 6 MIM 01/0721

6.4 Measuring electrodes

The MIM uses electrodes with galvanic tapping. They are in direct contact with the medium. The standard electrodes are made of stainless steel 1.4404.

In very rare cases (e.g. oils or fats in the metered medium), electrically insulating deposits on the meter electrodes cannot be ruled out. Such deposits would cause a failure of the meter.

In such cases, the electrodes must be cleaned with a soft brush and a grease solvent.

7. Mechanical connection

7.1 Check operating conditions

- flow rate
- max. operating pressure
- max. operating temperature

In general, MIM is subjected to the same loads as the piping into which it is installed. The MIM should therefore be kept away from extreme loads, such as pressure surges with strong, dynamic pipe movements, vibrations in the proximity of centrifugal pumps, high temperature media, flooding etc.

7.2 Installation


- Remove all packing materials and transport retainers and ensure that no such materials remain in the device.
- It can be installed in vertical, horizontal or rising pipes. Flow in direction of the arrow.
- Avoid pressure and tensile load.
- Mechanically secure the inlet and outlet pipe at a distance of 50 mm from the connections.
- Avoid valves or large reduction on the inlet section (this increases the inaccuracy of measurements).
- Check the leak tightness of the connections.




While mounting MIM hold the flowmeter from spanner surface (not from the housing) with the help of spanner.

Take into account the tightening torque.

Nominal size	Tightening torque
1/2"	22 to 24 Nm
3/4"	28 to 30 Nm
1"	28 to 30 Nm




Inlet and outlet run



Installation from top to bottom

avoid these installation locations



page 8 MIM 01/0721

8. Electrical Connection

8.1 General



Attention! Make sure that the voltage values of your system correspond with the voltage values of the measuring unit.

- Make sure that the supply wires are de-energised.
- Connect the supply voltage and the output signal to the plug PIN's as stated below.
- We recommend the use of wires with cross sectional area of min. 0.25 mm².





Attention! The measuring electrodes are galvanically connected with the reference potential of the supply voltage and the signal output.

8.1.1 Grounding/ Earthing

If the device is installed in a continuously grounded / earthed metallic pipe, no additional grounding / earthing of the housing is generally necessary. When installing in a plastic pipe or any ungrounded pipe, the housing must be earthed at the side threaded hole (M4) to ensure proper functionality of the MIM. If a class 2 switched-mode power supply (all-insulated, without an external protective earth connection) is used for the power supply, the grounding must be connected to ensure functionality. A M4 screw (thread length max. 8 mm), a matching washer, a ring cable lug and a toothed lock washer are required for correct installation.


These mechanical parts are not part of the delivery.





8.2 Pin assignment

8.2.1 External connection with electrical connector M12x1 4-pin for options C3T0 / Exx0 and Pxx0



8.2.2 Connection Exx0 / Pxx0 sensor

For the remote versions Pxx0 (PVC cable) and Exx0 (ETFE cable), the sensor and transmitter are delivered ex works with the cable connected.

The on-site installation may require dismantling the cable and reconnecting it later.



Note:

In principle, the cable can be shortened by the user on the transmitter side and connected to the transmitter again after appropriate assembly.




Attention!


A customer extension of the connection cable is not recommended because of the necessary continuous shielding and leads to malfunction of the device. The cable permanently connected to the sensor must not be disassembled.


page 10 MIM 01/0721

Wiring diagram Transmitter

Termination Connection cable (PVC and ETFE cable)








Insert pre-assembled cable through the cable gland and connect to the connector








Pull back the cable and put the contact spring on the outer shield




Push the cable into the cable gland, insert the plug connector and tighten the hexagon nut of the cable gland with SK key SW 19 and lock with SW 18

page 12 MIM 01/0721





Insert gasket, make sure gasket is seated correctly




Put the laminated seal disc on the screw and screw the threaded connection in the housing.

When tightening the screws, reduce the gap between sheet metal housing and the cover to ~ 0.5 mm



8.3 Connection example outputs:

OUT2: analogue output 4-20 mA OUT1: analogue output 0-10 V



Configurable output functions:


Out 1	Out 2
analogue output 4-20 mA	analogue output 4-20 mA
analogue output 0-20 mA	analogue output 0-20 mA
analogue output 2-10 V	analogue output 2-10 V
analogue output 0-10 V	analogue output 0-10 V
alarm output	alarm output
pulse output	pulse output
frequency output	frequency output
communication mode KofiCom	
communication mode IO Link	
control input	
control input dosing function	dosing output

page 14 MIM 01/0721

9. Operation and menu structure

9.1 General

9.1.1 Operation of the optical buttons



An optical button is located at each corner of the TFT display. The operability of the respective buttons is signaled by blue backlighting; therefore, non-backlit buttons are disabled and cannot be operated. To operate the keys, the finger must be placed on the key-dome and raised again. The orange background of the button symbols is briefly displayed in blue as visual feedback for a detected key press.

To avoid accidental operation in measuring mode, the operator must hold down the menu button for 3-5 seconds to activate the function. If the menu button is held down for more than 3 seconds, the blue backlighting will begin to flash to alert the user to release the button.

The operation of the optical buttons can also be done with gloves or other optically reflective objects. Suitable types of gloves are: cotton and textile gloves, light leather gloves, hygiene gloves made of latex and lightly rubberized work gloves. Black-coated work gloves of all kinds are not suitable. Light dirt on the surface usually does not interfere with the key function.

9.1.2 Function of the control buttons

The function of each control key can be recognized by the respective symbol

displayed in the corners of the TFT display.

		function			
key symbol	designation	Measuring mode	menu mode		
	menu mode	Activate menu mode hold 3-5 sec.	-		
Status	info display	opens the info menu	-		
	down	-	Scroll down menu / decrease numeric value when entering numeric value		
	up	-	Menu scroll up / Increase the number		

		function			
key symbol	designation	Measuring mode	menu mode		
			value for numeric		
			value input		
			Menu level lower /		
	forward	-	forward (last menu		
			level: Save value)		
			Menu function: menu		
	backward	-	level higher / back		
			(last step: exit menu)		

Soft key symbol "MENU" Soft key symbol "Status" active buttons Soft key symbol "Status"


9.2 Measuring mode

After applying the supply voltage, the device starts in measuring mode. In this mode, the measured values of the respective measuring variables are continuously recorded; the current instantaneous flow values, temperature values and the volume counter readings are cyclically calculated and displayed according to the type of display.

In addition to the main display, the states and configuration of the outputs are shown in the display. If the corresponding output is configured as an alarm output, the status is also displayed with a green or red background color. If the background color is green, the set threshold value is exceeded; if it is red, the current value is still under threshold.

page 16 MIM 01/0721

Measurement Mode Display Layout 'Single'



The measurement variables are represented by their corresponding symbols:


Menu entry	Mesuring variables Symbol	Description	
Flow	Q	Flow rate	
Volume	AC	Accumulated totalizer	
Temperature	T	Medium temperature	
Part volume	PT	Partial totalizer	

The outputs and their status are shown on the display as follows:

Output function OUT1/2	Symbol	Representation
disable	OFF	
Analog output 4-20mA	4-20mA	
Analog output 0-20mA	0-20mA	
Analog output 0-10V	0-10V	
Analog output 2-10V	2-10V	
Alarm output PushPull	SW+-	Background grey/green
Alarm output PNP	SW+	Background grey/green
Alarm output NPN	SW-	Background grey/green
Pulse output	PLS	
Frequency output	FRQ	
Communication mode	KofiCom	Use only for factory service
KofiCom (only OUT1)		
Communication mode	IO-Link	
IO-Link (only OUT1)		
Control input	X CTL	"X" symbol of the selected
		measuring variable

The measured variables flow, temperature and volume counter can in principle be assigned to each output function. The assignment of the respective output is indicated by the display of the symbol of the measuring variable. The representation of the assignment is independent of the set display layout (single, dual).

Measurement Mode Display Layout 'Dual'



9.2.1 Display area of the flow meters

The number of digits displayed on the volume counter display (partial and total volumetric counters) is limited to max. 8 digits. The partial and total volumetric meters therefore have a smaller font size than the flow and temperature display. If the 8-digit display range of the meter is exceeded, this is indicated by the display of 8 minus characters (-----). In this case, the meter reading can no longer be read. The user now has the option of bringing the counter reading back into the display area by changing the volume counter unit.

page 18 MIM 01/0721

9.3 Menu Mode

In menu mode, all device parameters can be set. The individual parameters are arranged in menu groups by function. While the menu mode is activated, the signal processing and the outputs are still active in the background. However, all display parameters and outputs are updated after exiting the menu mode or in the measuring mode.

<u>Note:</u> The menu mode will exit automatically after a certain time without using the buttons, if the parameter "Menu Timeout" is set not equal to "0".


9.3.1 Parameter setting

9.3.1.1 List Selection

Parameters with predefined selection values are defined by means of list selection. The currently selected menu item is displayed in orange text. The selection can be moved with the 🔼 🔽 keys, the key 🔤 is used to accept the selection.

To activate the menu mode, press the button for 3-5 seconds. The parameters are divided into main groups and subgroups.

The buttons $extbf{a}$ are used to select the main groups. In the main menu not all menu groups can be shown on the display at the same time, the list of individual menu items then scrolls up or down when the selection has reached the top or bottom. To choose the selection, the key $extbf{m}$ is pressed and the device jumps to the corresponding submenu or parameter setting level. For selecting of predefined parameter values $extbf{a}$ and $extbf{m}$ are used. After changing the value of the parameter and confirming with $extbf{m}$ the parameter is saved, and returns to the higher menu level. To return to the main menu or to exit the menu mode, press $extbf{m}$ (repeatedly).



9.3.1.2 Numerical value input

When setting parameters with a numerical value, the assigned unit is always displayed below the input field in square brackets in the input function. The maximum size and the number of decimal places is fixed and cannot be changed. After calling the input function, first the left, outer digit is displayed in orange. This position can now be adjusted either with the keys 🛋 💌 in the value from 0 to 9. By pressing the key 🔤, the entry point moves to the right and the next digit can be changed. By pressing the key 🚾, the editing point can be moved to the left again. If the editing point is on the far right, the set value is saved by pressing the key 🖂 again and switched to the higher-level menu function.

10. Device configuration

10.1 Sequence of device parameterization

The flowmeter MIM is pre-configured in factory. Changing the parameters "Measuring range" and "Sensor constant" or "K factor" is therefore not permitted. The adjustment of these parameters is only possible on the part of Kobold-factory. In the event of subsequent changes to volume or throughput units, the dependent parameters are converted and adjusted accordingly. However, the limit parameters of the switching outputs must always be checked and adjusted manually when adjusting volume or throughput units - these are not automatically converted.

An accidental change of the parameterization can be revised by the function "Reset factory setting" in the menu Userservice / Reset.

10.2 Language

In this menu item the menu language can be changed in English, German, French or Spanish (standard: English).

Parameter table language

Sublevel	parameter level	Sub- para- meter level 1	Sub- para- meter level 2	Sub- para- meter level 3	Description	Value range / value list	Standard value LPM version	Standard value GPM version
English					Selects English as the		English	
					menu language			
Deutsch					Selects German as the			
					menu language			
Francais					Selects French as the			
					menu language			
Espanol					Selects Spanish as the			
					menu language			

page 20 MIM 01/0721

10.3 Display

10.3.1 Refresh

Parameter "Refresh" defines the time interval within which the measuring variables are displayed. The "Refreshrate" can be increased in steps of 0.5 sec. to 10 sec. An increase in the refresh rate time causes an increased "filtering" of the display value.

10.3.2 Orientation

With the menu item "Orientation" the display can be rotated either clockwise or counterclockwise in 90 ° increments. As the display rotates, both the display contents and the function of the 4 control buttons are turned.


10.3.3 Layout

This parameter can be used to configure the display to either show one measurement variable or two measurement variables.

10.3.4 Display value

With the aid of this parameter, the measurement variables provided by the transmitter can be displayed. Depending on the 'Layout' display, either one or two measuring variables can be displayed.

10.3.5 Keys HOTKEYs




Two independent user keys are available, which can be individually assigned with different display functions. The 2 user keys are available in measurement mode top right and left. If the buttons are activated, they are backlit in blue and the programmed function can be executed by touching.

The following functions are available:

reading	MIN/MAX / Reset	Value display / Reset
flow	Yes / Yes	Yes / No
Temperature	Yes / Yes	Yes / No
Partial quantity counter	Not available	Yes / Yes
Totalizer	Not available	Yes / No

MIM-



10.3.6 Menu Timeout

The menu timeout time defines the time after which the menu function is automatically exited without pressing a key. In the setting "0 s" this function is deactivated and the menu function can only be left by hand by pressing the back key several times.

page 22 MIM 01/0721

Parameter table **Display**

Sublevel	Parameter level	Sub- para- meter level 1	Sub- para- meter level 2	Sub- para- meter level 3	Description	Value range/ value list	Default value LPM version	Default value GPM version		
Refresh	value input				Sets the display refresh rate	0.5-10 sec	0.5 sec			
Orientation	rotate CW				Rotates the display 90 ° clockwise		Landscape	10		
Onemation	rotate CCW				Rotates the display 90 ° counterclockwise		Lanascap	,,,		
Layout	Single				Shows a measured value in the display area		Double			
Layout	Double				Shows two measured value in the display area		Воиме			
display	Upper display	list selec-			Sets the reading for the upper display	Flow, volume,	Flow			
value	Lower display	tion		_	Sets the reading for the lower display	temperature, part volume	Temperature			
	Hotkeys -		Flow	List	Sets the reading and	Off, Value,				
			Volume							
		le	left	Tem- perature	selection	function for the left hotkey	Min / Max			
					Part					
			volume			Of	Off			
I/ a		right Flow Volume Tem- perature Part		Flow						
Keys						1:-4	Sets the reading and	Off Value		
			function for the right	Off, Value, Min / Max						
							hotkey	-		
	sensitivity	list selec- tion			Sets the sensitivity for the optical buttons	Low	Low			
Menu Timeout	value input		,		Defines the time after which the setting menu is automatically exited without pressing a key (0 = deactivated)	0.5 to 60 s	15 s			

10.4 Measurement

The Measurement menu lists the measurement variables that the transmitter provides. For magnetic inductive flowmeter, these are:

- Flow
- Volume (total volume counter)
- Temperature
- Part volume

Each measurement variable is still divided into its own submenu. In the submenu, all parameters relating to the respective measuring variables can be adjusted.

10.4.1 Flow

10.4.1.1 Unit

The displayed unit for the flow measurement can be selected from various predefined standard units. It is also possible to define a user-defined unit ("user"), here the "user unit" must be in LPM (liters / min.) be programmed:

e.g. Unit User = 100 LPM, if Q = 500 LPM then the display shows 5 users.

10.4.1.2 Filter function

The measured value filter filters the display value and most electrical output signals (analog outputs / frequency outputs / switching outputs).

A separately adjustable filter is available for each measured value (flow and temperature). In the factory setting, the standard filter with low filtering and active step detector is activated. Volume counters and pulse outputs are generally not filtered.

There are 3 different filter types available, so that a suitable filter functionality is available for as many applications as possible. The time base of the filter function is approx. 20 ms.

Filter type	Filter factor [n]	Step detector	Description
Standard	1 - 250	Yes	Rolling filter type, the size of the filter factor determines the number of temporarily stored and used averaging values. $MV_{AVG} = \frac{MV_0 + MV_{-1} + \cdots MV_{-n}}{n}$
IIR		No	With this filter type, depending on the filter factor, part of the last measured value average is added to the current average value. The filter corresponds to a digital low-pass filter of the 1st order with an infinite step response. The filter effect achieved is not linear to the parameter filter factor. A high filter effect is only achieved with filter values> 200. $MV_{AVG} = b*MV_0 + (1-b)*MV_{AVG-1}$ with $b = \frac{251-filter\ factor}{250}$
Exp. smoothing		No	The filter type works on the principle of exponential smoothing. The step response has an exponential course. The filter factor is proportional to the response time t_{90} of the step response. This enables the greatest filter effect to be achieved. $t_{90}{\sim}filter\ factor*75ms$ $MV_{AVG}=\frac{MV_{AVG-1}*(n-1)+MV_0}{n}$

with:

 MV_{AVG} = filtered measured value, MV_{AVG-1} = last filtered measured value, MV_0 = current measured value MV_{0-1} = last measured value

page 24 MIM 01/0721

Application areas of the filter types

Standard Standard filter with step detector with fast response time with

real changes in measured values. This filter type has a max.

time lag of filter factor * 20 ms

This filter smoothes slight to medium fluctuations in measurement values without the disadvantage of increasing the response time in flow monitoring

applications.

IIR Simple digital filter with lag, no step detector

This filter can be used for slight to medium pulsating fluctuations in measured values. With strong filtering, there is a correspondingly long lag of the filtered measured value in case of real measured value changes. Not suitable for flow monitoring applications with a large

filter factor.

Exp. Smoothing Simple smoothing filter with lag, no step detector

This filter can be used for strong pulsating fluctuations in measured values. With strong filtering, there is a long lag of the filtered measured value with real measured

value changes.

The lag can be determined via the filter factor to:

t₉₀ ~ filter factor * 75ms

Not suitable for flow monitoring applications with a large

filter factor.

Step detector (only available with standard filter)

The step detector integrated in the standard filter can detect the tendency of a real change in the measured value and temporarily bridge the filter function after detection of a step in the measured value in order to minimize the step response time. A step (sudden change) in the measured value can be detected both with increasing and with falling measured value. The step detector is set by the step threshold (*JD threshold*) and an interference suppression factor (*JD-ConfFactor*). The behavior at the beginning of the measuring range can be made "interference suppressed" with the parameter *O-ConfFactor*.

JD Threshold The value of the step threshold is normalized according to

the span of the measuring range, the default value 0.1

means 10% of the full scale value.

JD ConfFactor Defines the factor by which the step threshold must be

exceeded in succession without interruption before the step detector actually becomes active. If the end value of the interference suppression counter is not reached, it will be reset. However, if the final value of the counter is reached, the step detector is active and all filter buffers are overwritten

with the current measured value.

0-ConfFactor

If the measured values are at the start of the measuring range, below which the measured values are set to 0, the zero measured value suppression function may become active. The parameter 0-ConfFactor defines a counter value, how often the measurement range start value must fall short of in succession and without interruption before the measurement value is actually set to "0". This function serves to stabilize the measured value in the area of the start of the measuring range. Like the step detector, this function works in both directions, i. e. from measuring range \Rightarrow 0 and from 0 \Rightarrow measuring range.

Notes for applications with pulsating flows:

If pumps generate pulsating flow (e.g. peristaltic pumps or diaphragm pumps), the following instructions must be observed:

- The pulsation flow peaks must always be within the measuring range of the device
- If possible, install a pulsation damper
- The pulsation frequency of the pump should not be close to the 50 Hz frequency or its divider (25 Hz, 12.5 Hz, 6.25 Hz etc.), otherwise cyclical measurement fluctuations may occur.
- The measured value display (and the electrical analog and frequency outputs) can be most effectively dampened using the filter function "exp. Smoothing"

10.4.1.3 Separation

The parameter Separation sets the flow rate below which the measured value is set to "0". If this function is active, the flow value "0" is shown in blue colour in the display. If the parameter value is set smaller than the start of the measuring range (see technical data), the display value and all signal outputs assigned to it remain at "0" as long as the measured value does not exceed the start of the measuring range.

10.4.1.4 Simulation mode

See section 10.4.5

10.4.2 Volume

10.4.2.1 Counter type

Absolute:


Regardless of the flow direction, the calculated partial volume is added to the counters.

Bidirectional:

Depending on the flow direction, the calculated partial volume is added or subtracted to the counters. If the measured flow value is negative, the volume value goes down from measurement to measurement (possibly into the negative range).

page 26 MIM 01/0721

Volume measurement by different totalizer types



10.4.2.2 Unit of the total volume counter

The parameter "Unit" determines the volume unit of the total volume counter. The listed volume units are available. When changing the volume unit, the current counter reading is converted to the new volume unit.

It is also possible to define a user-specific unit "User". Here the "user unit" must be programmed in liters: e.g. unit "User" = 100 L, if the internal volume value reaches 500 L, then 5 "User" is shown on the display.

10.4.3 Temperature

10.4.3.1 Temperature Unit

The displayed unit for the temperature measurement can be selected from various default units. It is also possible to define a user-defined unit ("user"), in which case the "user unit" must be programmed in °C.

e. g. Unit "user" = $50 \, ^{\circ}$ C, if T = $50 \, ^{\circ}$ C then the display shows 1 user.

10.4.3.2 Simulation function

See section 10.4.5

10.4.4 Part Volume

10.4.4.1 Counter type

Absolute:

Regardless of the flow direction, the calculated partial volume is added to the counters.

Bidirectional:

Depending on the flow direction, the calculated partial volume is added or subtracted to the counters. If the measured flow value is negative, the volume value goes down from measurement to measurement (possibly into the negative range).

10.4.4.2 Unit of the part volume counter

The parameter "unit" defines the volume unit of all volume meters. The listed volume units are available. When changing the volume unit, the current counter readings are converted to the new volume unit.

It is also possible to define a user-specific unit "User". Here the "user unit" must be programmed in liters: e.g. unit "User" = 100 L, if the internal volume value reaches 500 L, then 5 "User" is shown on the display.

10.4.4.3 Memory reset

In this menu, the part quantity counter can be reset.

10.4.4.4 Simulation function

See section 10.4.5

10.4.5 Simulation function

With the simulation function, all available measured values can be simulated <u>independently</u> of each other for a <u>limited time</u>. The simulated measured values have full effect on the displays and outputs.


Each simulation started is automatically stopped after the time set in the "Sim Auto Stop Time" (user service) parameter (1 to 30 min) or after the programmed intervals have expired.

The following measured values can be simulated:

Volume flow, temperature and part quantity counter

The simulation starts as soon as the simulation is activated and the setting menu is exited. The simulation is interrupted or stopped, if the setting menu is called up. There are 3 different simulation types available for each purpose:

a.) "Triangle" mode




In "Triangle" mode, the simulation value increases continuously in the increment of the parameter "Increment value" and in the interval "Interval time" with the "Start value". After the amount of the parameter "intervals", the simulation value decreases again in the same way, in order to increase again. This

process is repeated continuously until the set time "Sim Auto Stop Time" has expired and the simulation ends.


page 28 MIM 01/0721

b.) "Monotonic" mode




In "Monotonic" mode, the simulation value increases continuously in the step size of the parameter "Increment value" and in the interval "Interval time" with the "Start value". After the amount of "Intervals" or the expiration of "Sim Auto Stop Time", the simulation ends.

c.) "Static" mode



In the "Static" mode, a constant value is output for the measured values flow and temperature. The simulation ends after the set simulation time.



In the "static" simulation for the part quantity counter, the counter is only changed once by the set "increment value" after the start.

When simulating the subset counter, note that in triangle mode, the submenu counter must be in bidirectional mode to achieve the expected effect.

Parameter table **Measuring**

		table Measur						
Sublevel	Para- meter level	Subpara- meter level 1	Sub- para- meter level 2	Sub- para- meter level 3	Description	Value range/ value list	Default value LPM version	Default value GPM version
Flow	Unit	List selection			Sets the flow unit	L/m, L/h, m3/h, galUS/m, galUS/h, galUK/m, galUK/h, L/s, mL/s, User	L/m	gals/m
		Туре	List selection Value input		See description	Default / IIR / exp. smoothing	standard	
		Filter factor				1-250	25	
	Filter	JD threshold				0.05 – 1.00 [xFs]	0.1	
		JD- ConfFactor				1-25	1	
		0-ConfFactor	-			1-25	1	
	sepa- ration	value input			Sets the value for the low flow cutoff	0 ≤ Value ≤ Range start	Range sta	nrt
	Simula- tion mode	See table Sim	ulation mo	de				
Volume	Counter Type	absolute/ bidirectional			Sets the counting mode		absolute	
	Unit	List selection			Sets the volume unit	ml, L, m3, galUS, galUK, User	L	L
	Unit	List selection			Sets the temperature unit	°C, °F, User	°C	°C
Tem- perature	Filter	Туре	List selec	tion	See description	Default / IIR / exp. smoothing	standard	
		Filter factor	Value inp	ut		1-250	1	
		JD threshold				0.05 – 1.00 [xFs]	0.1	
		JD- ConfFactor				1-25	1	
		0-ConfFactor				1-25	1	
	Simula- tions- modus	See table Simulation mode						
Part volume	Counter Type	absolute/ bidirectional			Sets the counting mode		absolute	
	Unit	List selection			Sets the volume unit	ml, L, m3, galUS, galUK, User	L	galUs
	memory reset	Yes/No			Sets the counter value to "0"			
	Simula- tion mode	See table Sim	ulation mo	de				

page 30 MIM 01/0721

10.5 Dosing function

see section 12

10.6 Outputs

The MIM flowmeter provides a total of 2 outputs that are freely configurable. The configuration of the outputs (output 1 and output 2) is done via a wizard function. The wizard function guides the user step by step through all necessary settings.

Steps:

- Select output
- Selection of the source or the measurement variable to be output (Flow, Volume, Temperature, Part volume)
- Selection of an output type (4-20 mA, 0-20 mA, 0-10 V, 2-10 V, alarm, pulse, frequency output,IO-Link, control input)
- Setting the output (scaling, thresholds)
- Save the configuration

The different output types are optimized for different types of applications. The following table contains the application recommendations for the different output types. If the outputs are not used according to the recommendations, measurement deviations can occur and the desired functionality is not achieved.

Application	Output type						
	Analog	Frequency	Pulse	Alarm			
	output (all	output	output	output			
	variants)						
Telemetry device	✓	✓					
Limit monitoring				✓			
Window monitoring				✓			
External dosage			✓				
External volumetric count			✓				

Application table output types


10.6.1 Alarm output

The alarm outputs can be parameterized with a limit value function or a window function.


10.6.1.1 Function

The parameter "Function" defines the basic function. Limit value function and window function are available.

Limit value function: The switching output is **active** if the current flow rate value is above the switching threshold. It remains **active** until the measured value has fallen below the switching threshold minus the hysteresis.



<u>Window function:</u> The switching output is **active** if the current flow measured value is outside a window, which is formed by the "switching threshold" and the "lower threshold". The monitored window decreases in each case by the amount of the "hysteresis". If the switching output is to be **active** within the window, the parameter "switching function" must be changed from N/O to N/C.



10.6.1.2 Output type

The parameter "Output type" defines the function of the transistor output. NPN, PNP or PP (push-pull) output types are available. The push-pull type combines NPN and PNP and is therefore the best choice for most circuits. All outputs are short circuit and overload protected.

10.6.1.3 Switching function

The "switching function" defines the mode of operation of the outputs. In the default setting "normally open", the output becomes active (switched) when the measured value exceeds the switching threshold. This feature is also referred to as N.O. In the "Normally closed" setting, the output below the switching threshold is already active and is deactivated when the measured value exceeds the switching threshold. This function is also referred to as N.C.

page 32 MIM 01/0721

10.6.1.4 Threshold

Threshold for limit value function and upper window point for window function.

10.6.1.5 Lower threshold

The "lower threshold" defines the lower limit when using the window function. When using the limit value function, this parameter remains ineffective.

The switching thresholds can be set both positive and negative.

10.6.1.6 Hysteresis


The appropriate setting of the "hysteresis" parameter ensures that the switching outputs do not switch on and off continuously when the current measured value fluctuates around the switching threshold. The hysteresis value should therefore always be greater than the real measured value fluctuations. As a result, a targeted suppression can be achieved.

10.6.1.7 Filter factor (delay)

Further suppression of the switching outputs of fluctuating measuring signals can be achieved by setting the parameter "Filter factor". If this parameter is selected greater than 0, the switching of the output will be delayed accordingly. The "Supp direction" parameter determines whether the deceleration is to be effective when the switching threshold is exceeded or not reached (alternatively in both directions). "High" means that the delay is active when the measured value exceeds the switching threshold, "Down" means corresponding effect when the switching threshold is undershot.

The measured value must stay continuously below or above the switching threshold with the count of [SUPPRESSIONFACTOR] before the switching output will be activated. With this function sporadic limit value overruns can be safely suppressed.

According to the value of the parameter "filter factor", the response time of the output generally increases.



Examples of the effect of the switching delay for window and limit function

10.6.2 Analogue outputs

10.6.2.1 Current output 0(4)-20 mA

The current output gives a measured variable (flow or temperature) in scaled form as a 0 (4) -20 mA current signal.

The current output is scaled via the "Value 20 mA "and" Value 4 mA "(with current output 0-20 mA "Value 0 mA"). By default, the "Value 20 mA" parameter is set to the value for the end of the measuring range, but can be parameterized as desired within the measuring range, but always bigger than the measuring range start value. The parameters "Value 4 mA" / "Value 0 mA" define the measured values for the starting current value, which may also be set freely in the measuring range. Note 1: If the value is set smaller than the end of the measuring range, the accuracy of the output voltage value is reduced.


Note 2: The burden on the current output must not exceed 500 Ω .


10.6.2.2 Voltage output 0-10 V / 2-10 V

The voltage output outputs a measurement variable (flow or temperature) in scaled form as a 0-10 V / 2-10 V voltage signal.

The scaling of the voltage output is done via the parameter "Value 10 V "and "Value 0 V". By default, the "Value 10 V" parameter is set to the value for the end of the measuring range, but can be parameterized as desired within the measuring range, but must always be bigger than the measuring range start value.


The parameters "Value 0 V" and "Value 2 V" define the measured values for the start voltage value, which may also be freely set in the measuring range.





Output behavior 4-20 mA and 2-10 V

page 34 MIM 01/0721



Output behaviour 0-20 mA and 0-10 V

10.6.2.3 Activation of behaviour according to NAMUR recommendation NE43

For all analogue outputs (current and voltage), the output behaviour can be activated according to NAMUR recommendation NE43. When the function is activated, e.g. the linear output of the 4 to 20 mA signals to 3.8 to 20.5 mA. Above 20.5 mA, the current value jumps to approx. 22 mA to signalise a measuring range overshoot. Current output values between 3.8 and 4.0 mA indicate that the measuring range is undershot. The output of approximately 3.6 mA signals a device or process fault (e.g., empty tube signalling).

10.6.3 Pulse output


MIM flowmeter provides a scalable pulse output. When the pulse output is activated, the cyclically incoming volume is available as a pulse train at the output. The pulse width of the pulse output is constant and can be set in a range of 1 ms up to 20 s. The pulse output is updated in a cycle of 20 ms. At the beginning of each update, it is determined how much volume has been accumulated during the previous update period. According to this amount and the set pulse volume, the corresponding amount of pulses is available as a pulse train at the output.



The pulse signal is not suitable for determining the volume flow with an external frequency measurement.




The reaction time of the pulse output is directly dependent on the flow parameter "separation" (cutoff). The shortest reaction time is reached if this parameter is set to the value "0.0" (factory setting: start of measuring range).



The electrical output type of the pulse output is push-pull, therefore HIGH and LOW are actively switched through at the output.

Pulse output function with different totalizer types



Behavior on OVERFLOW:

If the volumetric flow measurement is in the OVERFLOW range, the pulse output is switched off and a constant HIGH level is applied to the output. Generation of the output pulse train:

The pulse volume (pulse value volume per output pulse) can be set freely within wide ranges. Together with the adjustable pulse width and the measuring range of the device there is a limited range in which the pulse output is instantaneous.

This is the case if the following condition is met:

$$\frac{\text{MRE-Measurement Range End [L/min]*pulse width [ms]}}{\text{pulse volume [L]}} \leq 22500$$

or

$$Pulse\ volume\ [L] \geq \frac{\text{MRE-Measurement Range End [L/min]}*pulse\ width\ [ms]}{22500}$$

If the condition is not met, there may be a time lag of the pulse output. This is particularly undesirable if dosing tasks are to be performed with the pulse signal.

page 36 MIM 01/0721

The following table shows the different combinations of pulse volume and pulse width for the different measuring ranges, in which the above limiting condition is fulfilled.

Measuring range [LPM]	pulse width [ms]	min . pulse volume [L]	max. pulse rate [pulse/L]
	20	0.31111	3.21
350	10	0.15556	6.43
350	5	0.7778	12.86
	1	0.01556	64.29
	20	0.08889	11.25
100	10	0.04444	22.50
100	5	0.02222	45.00
	1	0.00444	225.00
	20	0.04444	22.50
50	10	0.02222	45.00
50	5	0.01111	90.00
	1	0.00222	450.00
	20	0.02222	45.00
25	10	0.01111	90.00
25	5	0.00556	180.00
	1	0.00111	900.00
	20	0.00889	112.50
10	10	0.00444	225.00
10	5	0.00222	450.00
	1	0.00044	2250.00
	20	0.0026	375
0.3	10	0.0013	750
03	5	0.0006	1500
	1	0.0001	7500
	20	0.00089	1125.00
01	10	0.00044	2250.00
01	5	0.00022	4500.00
	1	0.00004	22500.00

The pulse output only takes place in measuring mode; while the menu mode is active no pulses are given. The pulses accumulated in the menu mode are output as soon as the measuring mode is active again. Depending on the situation, this can also lead to a longer pulse lag.

10.6.3.1 Pulse volume

The parameter "Pulse volume" is defined as volume quantity for the output of a pulse; the unit is corresponding to [volume quantity / pulse]. The likewise common pulse rate [pulse / volume unit] corresponds to the reciprocal of the pulse volume. <u>Example:</u> Desired pulse rate at the output 10 pulses / liter => pulse volume = 1 / pulse rate = 1/10 L = 0.1 L

10.6.3.2 Volume unit

The volume unit to be set is the input unit for the "Pulse volume" parameter. The definition of a user-defined unit ("user") is also possible and can be programmed in "liters".

Example:

Unit "user" = 10 [L], pulse volume = 2 [user]

The total pulse volume would be 2 * 10 = 20 [L]. After 20 liters, a pulse is output.

10.6.3.1 Pulse width


The pulse width of the pulse output is flexibly adjustable from 1 to 20,000 ms.

10.6.4 Frequency output

The MIM flowmeter provides a scalable frequency output. When this output is activated, the measurement variable (flow or temperature) associated with the frequency output is output proportionally as a frequency with a 1: 1 pulse / pause duration. The output frequency at the end of the measuring range can be set (parameter "maximum frequency"). With the two parameters "Value for 0 Hz" and "Value for max Hz", the frequency output in the measuring range can be freely scaled.

Behavior on OVERFLOW:

If the measured value is in the overflow range, a constant frequency is output.



Output behavior Frequency output

page 38 MIM 01/0721

10.6.5 Control input

Output 1 can be configured as a control input. This can reset the MIN / MAX memory or the partial quantity counter depending on the assigned measurement variable.

Function	Measurement variable	Control pulse duration
MIN/MAX Reset	Flow, temperature	$0.5s < t_{high} < 4s$
Part volume counter reset	Part volume counter	$0.5s < t_{high} < 4s$

Parameter table Output 1/2 - Flow

Sub-parameter level 1	Sub- parameter level 2	Sub- parameter level 3	Description	Value range / value list	Standard value LPM version	Standard value GPM version
disabled			Output deactivated		IO-Link	
	Function		Sets the basic function	Limit function / window function	Limit function	ı
	Output	List selection	Sets the electr. Output	NPN/PNP/PP	NPN	
	switching function		Set the log. switching function	NO/NC	NO	
	threshold		Sets the switching threshold	MB start ≤ value ≤ Full scale	1	
Alarm output	lower threshold		Sets the lower threshold for window function	Value threshold ≤ value ≤ MB start	1	
	hysteresis		Defines the switching hysteresis	0 ≤ value ≤ (MB end – MB start)	1	
	filter factor		Factor for the switching delay x100 ms	0x ≤ value ≤ 60x	0	
	direction		Defines the effective direction of the switching delay	Up / Down / Both	Down	
	NAMUR Standard		Activates the behaviour according to NAMUR NE43	activated / deactivated	deactivated	
4-20 mA	Value 4 mA		Measured value for 4 mA output	MB-start ≤ value ≤ Wert 20 mA	0	
	Value 20 mA		Measured value for 20 mA output	Value 4 mA ≤ value ≤ Full scale	Full scale	
	NAMUR Standard	Value input	Activates the behaviour according to NAMUR NE43	activated / deactivated	deactivated	
0-20 mA	Value 0 mA		Measured value for 0 mA output	MB start ≤ value ≤ value 20 mA	0	
	Value 20 mA		Measured value for 20 mA output	Value for 0 mA ≤ value ≤ Full scale	Full scale	
	NAMUR Standard		Activates the behaviour according to NAMUR NE43	activated / deactivated	deactivated	
2-10 V	Value 2 V		Measured value for 2 V output	MB start ≤ value ≤ value 10 V	0	
	Value 10 V		Measured value for 10 V output	Value for 2 V ≤ value ≤ Full scale	Full scale	
	NAMUR Standard		Activates the behaviour according to NAMUR NE43	activated / deactivated	deactivated	
0-10 V	Value 0 V		Measured value for 0 V output	MB start ≤ value ≤ value 10 V	0	
	Value 10 V		Measured value for 10 V output	Value for 0 V ≤ value ≤ Full scale	Full scale	

page 40 MIM 01/0721

Sub-parameter level 1	Sub- parameter level 2	Sub- parameter level 3	Description	Value range / value list	Standard value LPM version	Standard value GPM version
	max. frequency		Frequency output at "value at max. Hz"	50-1000 Hz	500 Hz	
Frequency	overflow	Value input	Overflow value in % of the value "max.frequency"	1-100 [%]	1%	
output Value at 0	Value at 0 Hz		Value at 0 Hz	MB start ≤ value ≤ value at max. Hz	0	
	Value at max. Hz		Value at "maximum frequency"	Value for 0 Hz < value ≤ Full scale	Full scale	
Control input (only output 1)			Control function for MIN / MAX memory reset	OFF, memory reset	Aus	
KofiCom	Factory calibration mode on output 1					
IO-Link	This mode active	ates the IO-Link	function on output 1(standa	ard factory setting)		

Parameter table Output 1/2 – Volume

Sub- parameter level 1	Sub- parameter level 2	Sub- parameter level 3	Description	Value range / value list	Standard value LPM version	Standard value GPM version
disabled			Output deactivated		disabled	
	Pulse unit	List selection	Sets the Pulse Volume for Pulse Volume	ml, L, m3, galUS, galUK, User	L	galUs
Pulse output	Pulse volume	value input	Sets the value for the pulse volume	0.001-999	1	
	Pulse width		Sets the pulse width	1-20.000	1 ms	
KofiCom	Factory calibration mode on output 1					
IO-Link	This mode ac	tivates the IO-L	ink function on οι	utput 1		

Parameter table **Output 1/2 – Temperature**

Sub- parameter level 1	Sub- parameter level 2	Sub- parameter level 3	Description	Value range / value list	Standard Standard value LPM value GPM version version	
disabled			Output deactivated		disabled	
	Function		Sets the basic function	Limit function / window function	Limit function	
	Output	List selection	Sets the electr. Output	NPN/PNP/PP	NPN	
	Switching function		Sets the log. switching function	NO/NC	NO	
	Threshold		Sets the switching threshold	MB start ≤ value ≤ Full scale	1	
Alarm output	lower threshold		Sets the lower threshold for window function	Value threshold ≤ value ≤ MB start	1	
	Hysteresis		Defines the switching hysteresis	0 ≤ value ≤ (MB end – MB start)	1	
	Filter factor		Factor for the switching delay x100 ms	0x ≤ value ≤ 60x	o	
	Direction		Defines the effective direction of the switching delay	Up / Down / Both	Down	
NAMUR Standard			Activates the behaviour according to NAMUR NE43	activated / deactivated	deactivated	
4-20 mA	Value 4 mA		Measured value for 4 mA output	MB start ≤ value ≤ value 20 mA	0	
	Value 20 mA		Measured value for 20 mA output	Value 4 mA ≤ value ≤ Full scale	Full scale	
0-20 mA	NAMUR Standard	Value input	Activates the behaviour according to NAMUR NE43	activated / deactivated	deactivated	
0-20 IIIA	Value 0 mA		Measured value for 0 mA output	MB start ≤ value ≤ value 20 mA	0	
	Value 20 mA		Measured value for 20 mA output	Value 0 mA ≤ value ≤ Full scale	Full scale	
0.40.1/	NAMUR Standard		Activates the behaviour according to NAMUR NE43	activated / deactivated	deactivated	
2-10 V	Value 2 V		Measured value for 2 V output	MB start ≤ value ≤ value 10 V	0	
	Value 10 V		Measured value for 10 V output	Value 2 V ≤ value ≤ Full scale	Full scale	
	NAMUR Standard		Activates the behaviour according to NAMUR NE43	activated / deactivated	deactivated	
0-10 V	Value 0 V		Measured value for 0 V output	MB start ≤ value ≤ value 10 V	0	
	Value 10 V		Measured value for 10 V output	Value 0 V ≤ value ≤ Full scale	Full scale	

page 42 MIM 01/0721

Continuation Parameter table **Output 1/2 – Temperature**

Sub- parameter level 1	Sub- parameter level 2	Sub- parameter level 3	Description	Value range / value list	Standard value LPM version	Standard value GPM version
Frequency output	max. frequency	. Value input	Frequency output at "value at max. Hz"	50-1000 Hz	500 Hz	
	Overflow		Overflow value in % of the "value at max. frequency"	1-100 [%]	1%	
	Value at 0 Hz		Value at 0 Hz	MB start ≤ value ≤ value for max. Hz	0	
	Value at max. Hz		Value at "max. frequency"	Value for 0 Hz < value ≤ Full scale	Full scale	
Control input (only OUT1)			Control function for MIN / MAX memory reset	OFF, memory reset	OFF	
KofiCom (only OUT1)	Factory calibration mode on output 1					
IO-Link (only OUT1)	This mode activ	ates the IO-Link	function on output 1			

Parameter table Output 1/2 - Part volume

Sub- parameter level 1	Sub- parameter level 2	Sub- parameter level 3	Description	Value range / value list	Standard value LPM version	Standard value GPM version
Disabled			Output deactivated		disabled	
D. Inner de d	Pulse unit	List selection	Sets the Pulse Volume for Pulse Volume	ml, L, m3, galUS, galUK, User	L	galUs
Pulse output	Pulse volume	Value input	Sets the value for the pulse volume	0-999	1	
	Pulse width	•	Sets the pulse width	1-20.000	1 ms	
Control input (only Out1)			Control function for counter reset	OFF, memory reset	Off	
KofiCom (only OUT1)	Factory calibration mode on output 1					
IO-Link (only OUT1)	This mode ac	tivates the IO	-Link function on output	<u>†</u> 1		

10.7 User service

The user service provides the user with a reset function and password setting. Together with the activation of a user password, therefore, the menu access for the user on the part of a master user can be blocked.

10.7.1 User service / change password

In the factory setting the user password is set to "00000", the user functions are thus freely accessible. If the user password is changed to other than "00000", the password prompt becomes active the next time the user menu is entered. If the set password is no longer known, a master password can be requested from KOBOLD.

10.7.2 User service / factory setting

By activating this function, the user can reset the device to the factory settings. Any user settings will then be lost and the device will be back in delivery condition.

Parameter table User menu

Sublevel	Parameter level	Description	Value range / value list	Standard value LPM version	Standard value GPM version
Password	value input	Protects the user service menu by password prompting if the password is not "00000"	00000-99999	00000	
Factory reset	Yes / No	Resets the device to factory settings			
Menu lock	unlocked / closed	With "locked", the menu access only takes place via the password prompt	unlocked / closed	unlocked	
Sim Autostop	Value input	Sets the time for how long the simulation mode remains active	1 - 31 min.	10 min.	

page 44 MIM 01/0721

10.8 Service / Factory service

The factory service function is password protected and not accessible to the user.

10.9 Info

10.9.1 **General**

This info option displays the measuring ranges of the device for flow and temperature.

10.9.2 **Version**

This info option displays the hardware and software version of the device.

10.9.3 QR code link to the user manual

Here a QR code is displayed. With a suitable smartphone, the code can be scanned and the user manual in English language downloaded directly as a PDF and opened.

The smartphone must have a QR code scanning app and a PDF reader app installed, as well as an internet connection.

Parameter table Info

Menu level	Sublevel	Description
	General	Displays the measuring ranges of the device
Info	Version	Displays the hardware and software version
	Manual	Displays the QR code to download the instruction manual

10.10 Device default settings

The MIM flowmeter is factory set and unloaded with the following configuration:

Display - Dual

Upper display - Flow

Lower display - Temperature

Out 1: IOLINK

Out 2: OFF





Important note for MIM devices powered with software REV190320:

If output 1 should be operated as a current output, the conversion of the output from IOLINK (factory setting) to current output must be made before the electrical connection of the current loop. If this is not observed, the access to the menu function is blocked and the device can no longer be configured.

11. Status

The electromagnetic flowmeter can detect and display various device or application errors.

If there is a status or error message, the STATUS symbol in the display alternately flashes orange / red. To call up the status / error information, the status key must be pressed, then the status window that appears then lists all the messages that have accumulated up to this point in time. By pressing the $\checkmark \checkmark \checkmark \cdots$ key, the user confirms the knowledge of the displayed errors, the status memory is cleared and the status window is closed. If one of the displayed errors persists, it will be reported again by flashing the status icon.

The following status / error messages are generated:

Display text	Description	Debugging
Empty Pipe	Measuring tube is not completely filled with medium or medium with too low conductivity is used.	Check the filling of the measuring circuit or conductivity of the medium (> 20 µs / cm)
Temp Sens Error	Error in the temperature measuring circuit	Repair by KOBOLD Service necessary
Meas saturated	Flow measuring circuit overdriven	Reduce flow rate
No Subslave	Internal hardware error	Repair by KOBOLD Service necessary
Simulation	Simulation function active	-

page 46 MIM 01/0721

12. Dosing function

The standard MIM provides a simple dosing function. This can be permanently activated or deactivated in the settings menu under the menu item "dosing". If the dosing function is activated, fixed functions are assigned to the 2 outputs which cannot be changed as long as the dosing function is activated:

OUT2 (Pin 2): Dosing output in push pull configuration


OUT1 (Pin 4): Control input for START/STOP/RESET function



Attention!

When the control input is used, then OUT1 (connection pin 4) must be always polarised, either to the 24 Vdc or to the GND (pin 3). When using a mechanical button that switches the supply voltage to the control input, a 10 kOhm pull-down resistor is recommended. The control input must not be left open!

If the dosing function is deactivated, both outputs are switched to OFF (deactivated) by default, but can then be freely configured again.



In the main display of the dosing function, the quantity to be dosed in a preselectable unit and the current flow value are displayed on the one hand. The progress of the dosing process is additionally represented by a graphic animation in which the container shown fills in percent and also overfill is shown.

<u>Softkey buttons:</u> All softkey buttons in dosing mode must be held down by the user for at least 2 seconds and then released again for the corresponding function to be triggered. This is to avoid accidental operation.

<u>Control input:</u> Connection OUT1 can be used as a control input for the functions Start / Stop / Reset when the dosing function is activated.

Function	Conditions	Control pulsetime
START	Stop Modus	$0.5 \text{ s} < t_{high} < 4 \text{ s}$
STOP	Run Modus	$0.5 \text{ s} < t_{high} < 4 \text{ s}$
RESET	Stop Modus	t _{high} > 5 s

START of dosing:

Dosing can be started either by triggering the "START" softkey or by applying a high pulse to the control input.

After the START function has been triggered, the dosing output is switched to active (High) and the dosing counter is counted down in the standard direction when flow is present.

If the dosing process is stopped incompletely by hand, it can be restarted by the START function.

STOP of dosing


If the dosing process is started, it can be stopped or interrupted by the STOP function. Resumption of dosing to reach the total dosing quantity is possible by START

Like the START function, the STOP function can be remotely controlled by the control input.

RESETTING the dosing value

If the dosing process is finished or stopped, the dosing quantity can be reset to the default value by the function RESET.

This function can also be triggered at the control input.



page 48 MIM 01/0721

Description of dosing parameters

Dosing quantity "Value"

Parameter "Value" determines the dosing volume. The volume unit is specified in the "Unit" parameter.

The maximum size is limited to 9999.9 (one digit after the decimal point). The absolute quantity can be extended or restricted by a suitable choice of dosing unit.

Dosing unit "Unit"

Parameter "Unit" defines the dosing volume unit. The choices are: mL, L, m3, galUS, galUK, barrel, user

Dosing correction value "Correction value"

The "Correction value" parameter can be used to correct a system-related, constant "incorrect dosing" without having to change the actual dosing quantity. The correction value can be both positive and negative. If the system doses a smaller volume than intended, the correction value must be positive, but negative for a larger real volume. e.g.

Dosing quantity = 10 L

Correction value = -1 L

In this case, the metering counter will count from 10 L to '0', but will stop at 1 L because the quantity to be metered is 9 L calculated on the basis of the correction value of -1 L.

With a correction value of +1 L, the dosing counter will stop counting at -1 L, because the dosing amount is calculated to be 11 L.

10 - (-1 L) = 11 L

The adjustable value of the correction value must always be:

(Value + Correction Value)> 0

If this condition is not met, this will be indicated by a warning message and the correction value will be preset to the value - (Value-0.1).

Dosing parameter "Timeout"

During the dosing process, the presence of a flow value not equal to 0 is constantly monitored. For this purpose, the parameter "Timeout" is used to set the time after which the status message "Time Out" is triggered.

The timeout value can be set between 0.5 sec and 10 sec.

Parameter table **Dosing**

Sublevel	Parameter level	Subpara- meter level 1	Subpara- meter level 2	Subpara- meter level 3	Description	Value range / value list	Standard value LPM version	Standard value GPM version
	disabled				Dosing function deactivated		disabled	
		Activation			Dosing function activated		uisableu	
		Value	Value input			0 ≤ Value ≤ 9999.99 [unit]	0	
Activation	activated	Correction value	Value input			-999.99 ≤ Value ≤ +999.99 [unit]	0	
		Unit	List selection			ml, L, m3, galUS, galUK, User	L	galUs
		Time out	Value input			0.5 - 10 sec	0.5 sec.	

13. IO-Link function

As of firmware version REV190320, the MIM flowmeter has an IO-Link communication interface as standard. Process and diagnostic data can be accessed directly via this interface and the device can be parameterized.

Output 1 is factory configured for IO-Link function. If the IO-Link communication mode is active, the "IOLINK" symbol in the status display for the outputs is displayed in green. The setup menu remains locked when the IOLINK mode is active and is inaccessible.

To ensure that the IO-Link device can be operated correctly on the connected IO-Link master, it is necessary to install the device description file matching the device.

The device description files (IODD) are available in the IODDfinder database under ioddfinder.io-link.com. There may be different IODD versions available for devices of the same type. To select the correct IODD, the device ID can either be read out via the connected IO-Link master or, alternatively, identification can be made using the device's firmware identifier.

page 50 MIM 01/0721

The IODD assignment can be found in the following table.

Firmware ID	Product type	Device-ID	Device-ID	Remarks
		[hex]	[dec]	
V01.0_Rxxxxxx	-	-	-	No IO-Link
				function
V01.1_Rxxxxxx	MIM Compact up to 1 inch	0x010100	65792	-
	MIM Compact 2 inch	0x010200	66048	-
	MIM Remote up to 1 inch	0x010300	66304	-
	MIM Remote 2 inch	0x010400	66560	-
V01.11_Rxxxxxx	MIM Compact up to 1 inch	0x010600	67072	-
	MIM Compact 2 inch	0x010700	67328	-
	MIM Remote up to 1 inch	0x010800	67584	-
	MIM Remote 2 inch	0x010900	67840	-

How to download the correct IODD:

- Read out the firmware ID of the device from the INFO menu
- Find out the device ID (decimal) from the table above according to the firmware identification and the product type
- In the IODD finder, identify the correct IODD using the Device ID column and download the associated ZIP file using the download button.

If the device is operated on an IO-Link master with port class A, only a maximum output current of 50 mA may be drawn from output 2 (OUT2) (current or binary output), otherwise the IO-Link master will be overloaded and it can cause malfunctions.

13.1 Specification

Manufacturer ID 1105 (decimal), 0x0451 (hex)

Manufacturer name Kobold Messring GmbH

IO-Link specification V1.1
Bitrate COM3
Minimum cycle time 1.1 ms

SIO mode yes (OUT1 in configuration IO-Link)

Block parameterisation yes
Ready for operation 10 sec.
Max. cable length 20 m
IO-Link master port class A

14. Technical Information

Measurement process: electromagnetic see order details Range: Media: conductive fluids

Minimum conductivity: ≥20 µS/cm $70 \text{ mm}^2/\text{s}$ Max. medium viscosity: 16 bar Max. pressure:

<±(0.8% of reading+0.5% of full scale)* Accuracy:

±0.2% of full scale Repeatability:

Response time flow t₉₀

<100 ms (alarm/pulse/frequency output): (analogue output): <1 s

Temperature measurement

PT1000 Sensor:

 $\leq \pm 2$ °C (flow > 0.2 m/s) Accuracy:

Measuring range: Response time of temperature tg0 temperature range of medium

(signal output): <20 s

Mounting position: in all directions In-/outlet: 3 x DN/2 x DN Pressure drop (max at ME) MB 01 110 mbar

MB 05 400 mbar MB 10 50 mbar

250 mbar (3/4"), 30 mbar (1") MB 15

MB 20 110 mbar MB 40 450 mbar MB 35 120 mbar

Handling: 4 optical touch fields, useable with hand gloves**

stainless steel 1.4404, Housing: display screen PMMA

Wetted parts

Connection fitting and housing: stainless steel 1.4404

Insulation parts: **PFFK**

Electrodes: stainless steel 1.4404

Seals: FKM: MIM-12xxx; EPDM: MIM-13xxx

Protection: **IP 67**

Temperature ranges

Design	Electronic	Model	Seals material	Media temperature	Ambient temperature	
	СОТ	MIM-12	FKM	-20 °C +70 °C	00.00	
compact version	C3T MIM-13		EPDM	-20 °C +70 °C	-20 °C +60 °C	
remote version	P020	MIM-12 MIM-13	FKM	-20 °C +85 °C	-20 °C +60 °C (display electronic)	
(PVC cable)			EPDM	-20 °C +65 °C	-20 °C +85 °C (sensor)	
	version E02 ¹⁾	MIM-12	FKM	-20 °C +140 °C	-20 °C +60 °C (display electronic)	
remote version			FRIVI	-20 C +140 C	-20 °C +140 °C (sensor)	
(ETFE cable)	E02 ⁷	MIN 40	EDDM	-40 °C +140 °C	-20 °C +60 °C (display electronic)	
		MIM-13	EPDM	-40 C +140 C	-40 °C +140 °C (sensor)	

page 52 MIM 01/0721 **Electrical data**

Supply voltage: 19-30 Vpc, internal power consumption

max. 200 mA (without outputs)

Display: TFT display, 128 x 128 pixels,

1.4" display orientation in 90° steps adjustable

Display repetition rate: 0.5 ... 10 s, adjustable

Pulse output Push-Pull, freely scalable, configurable for

partial or accumulated totalizer

Frequency output Push-Pull, freely scalable,

Overflow frequency adjustable

Alarm output: NPN, PNP, Push-Pull,

configurable max. 30 V_{DC},

max. 200 mA short-circuit proof

Analogue output: active, 3 wire, 0(4)-20 mA,

max. load 500 Ω or 0-10 VDC, (R_i = 500 Ω)

Control input (MIN / MAX / partial volume RESET)

OUT1, high active 0 <ULow <10 VDC 15 VDC <UHigh <Vs

No internal pull-ups available, active high / low signal necessary!

Total and partial quantity counter: overflow (reset) at 15 * 10⁶ liters

(regardless of the set unit)

Electrical connection: plug M12x1, 4-pin

Dosing Function

Dosing value: 0.1 ...9999.9 [*Unit*]

Dosing output OUT2

PushPull, High active

Control input: OUT1, High active

 $0 < U_{Low} < 10 V_{DC}$ 15 V_{DC} < $U_{High} < V_{S}$

No internal pull-ups available, active high / low signal necessary!

START/STOP pulse: $0.5 \text{ s} < t_{high} < 4 \text{ s}$


RESET pulse: $t_{high} > 5 s$


¹⁾ Cable length 02=2m, 05=5m, 10=10m, 15=15m, 20=20m

 $^{^*}$ Under reference conditions: media temperature: 15 °C ... 30 °C, 1 cSt, 500 μ S/cm, 1 bar ambience temperature: 15 °C ... 30 °C

^{**} Limited functionally with black rubber gloves

Pressure Loss





page 54 MIM 01/0721

15. Order Codes

Order Details (Example: MIM-12 05G G4 C3T 0)

Model	Measuring Range ¹⁾	Native Connection	Electronics	Options	
	01G = 0.1616 GPH	G2. . = G 1/4 Male			
	01H = 0.011 LPM	G2 = G 1/4 IVIale			
	03G = 0.4848 GPH				
	03H = 0.033 LPM	G4 ³ = G 1/2 Male	C3T = Compact TFT Display		
	05G = 0.012.6 GPM		2x Configurable Outputs (Current/Voltage/Pulse/		
MIM-12 = SS Housing	05H = 0.0410 LPM		Frequency/Alarm)		
SS Electrode	10G = 0.0256.6 GPM		M12x1 Electrical Connection	0 = Without	
FKM Seals	10H = 0.125 LPM	G5 ³ = G 3/4 Male	P02 ² = Remote Display Version, TFT Display, 2m PVC Cable,	$\mathbf{K}^{4)} = \text{Including}$	
	15G = 0.0513 GPM	G5 % = G 3/4 Male		Calibration	
MIM-13 = SS Housing SS Electrode	15H = 0.250 LPM		Max. 185 °F	Report	
EPDM Seals	15G = 0.0513 GPM				
	15H = 0.250 LPM	203) 0.4 Mails	E02 ²⁾ = Remote Display Version,		
	20G = 0.126 GPM	$G6^{3} = G 1 Male$	TFT Display, 2m ETFE Cable, Max. 284 °F		
	20H = 0.4100 LPM				
	35G = 0.490 GPM	N9 = 2" NPT Female			
	35H = 1.5350 LPM	G9 = G 2 Male			
Accessories: P/N 807.037 = 4-Pin Micro-DC Connector with 6-foot Cable P/N 807.037/5M = 4-Pin Micro-DC Connector with 16-foot Cable P/N 807.037/10M = 4-Pin Micro-DC Connector with 32-foot Cable					

¹⁾ Temperature units of measure factory programmed; °C for LPM models and °F for GPM/GPH models

Accessories

Description	Model	Image
Stainless steel wall mounting kit for remote version (2 brackets, without nuts/washers)	ERS-ZOK-023618	

Description	Model	Dimensions [mm]	Image
Clamping bracket set for wall mounting (stainless steel with partial polyolefin sleeve)	ZUB-MIM225128	15x6.5 100	

²⁾ Order code substitution for longer cables: **020** = 2 m (6 ft), **050** = 5 m (16 ft), **100** = 10 m (32 ft), **150** = 15 m (49 ft), **200** = 20 m (65 ft). Wall mounting brackets (brackets incl. accessories) are included in the scope of delivery.

³ Regulation (EC) No. 1935/2004 for materials and articles intended to come in contact with food. Not for connection code G9/N9

⁴⁾ Please specify number of measuring points in clear text

Order Details MIM Fitting Sets Accessory Kits*

Accessory kit number	Meter connection	Process connection	Fitting set type
ZUB-AD2U15P08	G ½ cap nut	1/4" NPT male	Cap nut and union
ZUB-AD2G08P08	G ¼ female	1/4" NPT male	Cap nut and union
ZUB-AD2G15P15	G ½ female	½" NPT male	Adapter
ZUB-AD2G15N08	G ½ female	1/4" NPT female	Adapter
ZUB-AD2G15N15	G ½ female	½" NPT female	Adapter
ZUB-AD2U20P15	G ¾ cap nut	½" NPT male	Cap nut and union
ZUB-AD2G20P20	G ¾ female	3/4" NPT male	Adapter
ZUB-AD2G20N15	G ¾ female	½" NPT female	Adapter
ZUB-AD2G20N20	G ¾ female	3/4" NPT female	Adapter
ZUB-AD2U25P15	G 1 cap nut	½" NPT male	Cap nut and union
ZUB-AD2U25P20	G 1 female	3/4" NPT male	Cap nut and union
ZUB-AD2G25N15	G 1 female	½" NPT female	Adapter
ZUB-AD2G25N20	G 1 female	3/4" NPT female	Adapter
ZUB-AD2G25N25	G 1 female	1" NPT female	Adapter
ZUB-AD2G25T25	G 1 female	1" Tri-Clamp®	Adapter
ZUB-AD2G50T50	G 2 female	2" Tri-Clamp®	Adapter


^{*} Note: All fitting kits include 2x Klinger SIL® flat sealing gaskets or 2 x FKM O-rings (for ZUB-AD2G50T50)


page 56 MIM 01/0721


16. Dimensions


[mm]
Compact version


G	
1/4	
1/2	
3/4	
1	
















Remote version Without wall mounting brackets



With wall mounting brackets



page 58 MIM 01/0721

17. Appendix

17.1 IO-Link process data structure

Process data length: 9 bytes

Byte	Data	Bit count	Format	Factor	Range	Value
no.						
0 - 2	Flow	24 Bit	IntegerT	1/1000	+/-8388,608	L/min
3 - 6	Volume	32 Bit	FloatT		+/-1,4*10 ⁻⁴⁵ +/-3,4*10 ⁺³⁸	L
7 - 8	Temperature	12 Bit	IntegerT	1/10	+/-204,8	°C
	reserved	1 Bit	BooleanT			
	reserved	1 Bit	BooleanT			
	Status OUT1	1 Bit	BooleanT			
	Status OUT2	1 Bit	BooleanT			

Flow (24 Bit, IntegerT)	
0 1 2 3 4 5 6 7 0 1 2 3 4 5 6 7	0 1 2 3 4 5 6 7
Byte 0 Byte 1	Byte 2
Volume (32 Bit, FloatT)	
0 1 2 3 4 5 6 7 0 1 2 3 4 5 6 7	0 1 2 3 4 5 6 7 0 1 2 3 4 5 6 7
Byte 3 Byte 4	Byte 5
Temperature (12 Bit, IntegerT)	

17.2 IO-Link diagnosis information

Event Code [hex]Event Code [dec]NameDevice StatusTypeDefinition0x771030480Short CircuitErrorcheck installation0x8C1035856Process Variable Range OverrunWarningprocess data uncertain0x8C2035872Measurement Range OverrunErrorcheck application0x8C3035888Process Variable RangeWarningprocess data uncertain0x183862001. Test Event For Protocol TestingErrorfirst test event first test event first test event for Protocol Testing0x183962012. Test Event For Protocol TestingErrorsecont test expected flow measuring f	nt event ing in
0x771030480Short CircuitErrorcheck installation0x8C1035856Process Variable Range OverrunWarningprocess data uncertain0x8C2035872Measurement Range OverrunErrorcheck application0x8C3035888Process Variable Range UnderrunWarningprocess data uncertain0x183862001. Test Event For Protocol TestingErrorfirst test eve0x183962012. Test Event For Protocol TestingErrorsecont test executes e	nt event ing in
0x8C1035856Process Variable Range OverrunWarningprocess data uncertain0x8C2035872Measurement Range OverrunErrorcheck application check appli	nt event ing in
0x8C2035872Measurement Range OverrunErrorcheck application0x8C3035888Process Variable Range UnderrunWarningprocess data uncertain0x183862001. Test Event For Protocol TestingErrorfirst test eve0x183962012. Test Event For Protocol TestingErrorsecont test executes execut	nt event ing in
0x8C2035872Measurement Range OverrunErrorcheck application0x8C3035888Process Variable Range UnderrunWarningprocess data uncertain0x183862001. Test Event For Protocol TestingErrorfirst test event0x183962012. Test Event For Protocol TestingErrorsecont test end0x183A6202Flow MRE OverrunWarningflow measuring0x183B6203Flow MRS UnderrunWarningflow measuring0x183C6204Flow Overflow Overrun2Warningflow overflow range overrung0x183D6205Flow Underflow Underrun2Warningflow underflow range underrung	nt event ing in
0x8C3035888Process Variable Range UnderrunWarningprocess data uncertain0x183862001. Test Event For Protocol TestingErrorfirst test eve0x183962012. Test Event For Protocol TestingErrorsecont test e0x183A6202Flow MRE OverrunWarningflow measuring range overrung0x183B6203Flow MRS UnderrunWarningflow measuring range underrung0x183C6204Flow Overflow Overrun2Warningflow overflow range overrung0x183D6205Flow Underflow Underrun2Warningflow underflow range underrung	nt event ing in
Underrun Ox1838 6200 1. Test Event For Protocol Testing Ox1839 6201 2. Test Event For Protocol Testing Ox183A 6202 Flow MRE Overrun Ox183B 6203 Flow MRS Underrun Ox183C 6204 Flow Overflow Overrun Ox183D 6205 Flow Underflow Underrun Uncertain Error Secont test expected by the second test expected by th	nt event ing in
0x183862001. Test Event For Protocol TestingErrorfirst test event0x183962012. Test Event For Protocol TestingErrorsecont test executes test	event ing in
Testing Ox1839 6201 2. Test Event For Protocol Testing Ox183A 6202 Flow MRE Overrun Ox183B 6203 Flow MRS Underrun Ox183C 6204 Flow Overflow Overrun Ox183D 6205 Flow Underflow Underrun Testing Warning flow measuring flow measuring flow measuring flow measuring flow overflow frange underrun Warning flow overflow overflow flow overflow flow overflow flow overflow flow overflow flow overflow flow underflow underflow underflow underflow underflow underflow underflow flow underflow underfl	event ing in
0x1839 6201 2. Test Event For Protocol Testing Error secont test expected and second test expected and se	ing in
Testing Ox183A 6202 Flow MRE Overrun Ox183B 6203 Flow MRS Underrun Ox183C 6204 Flow Overflow Overrun Ox183D 6205 Flow Underflow Underrun Testing Warning flow measuring range overrun Warning flow overflow overflow overflow range overrun Warning flow overflow overflow overflow range overrun Warning flow underflow overflow overflow range overrun Warning flow measuring range underflow overflow overflow overflow range overrun Warning flow measuring range underflow overflow overflow overflow range overrun Warning flow measuring range underflow overflow overflow overflow overflow range overrun Ox183D 6205 Flow Underflow Underrun 2 Warning flow underflow underflow underflow underflow underflow overflow range underflow overflow range underflow underfl	ing in
0x183A6202Flow MRE OverrunWarningflow measure range overrun0x183B6203Flow MRS UnderrunWarningflow measure range undernown0x183C6204Flow Overflow Overrun2Warningflow overflow range overrun0x183D6205Flow Underflow Underrun2Warningflow underflow u	ing
0x183B 6203 Flow MRS Underrun Warning flow measure range understown and several range understown flow overflow overflow overflow range overrun 0x183C 6204 Flow Overflow Overrun 2 Warning flow overflow range overrun 0x183D 6205 Flow Underflow Underrun 2 Warning flow underflow range understown understown and several range understown and several	ing
0x183B 6203 Flow MRS Underrun Warning flow measure range undersome range undersome range undersome range undersome range undersome range undersome range overrun 0x183C 6204 Flow Overflow Overrun 2 Warning flow overflow range overrun 0x183D 6205 Flow Underflow Underrun 2 Warning flow underflow underflow undersome range range undersome range range undersome range range undersome range underso	ing
0x183C 6204 Flow Overflow Overrun 2 Warning flow overflow range overrun 0x183D 6205 Flow Underflow Underrun 2 Warning flow underflow un	_
0x183C 6204 Flow Overflow Overrun 2 Warning flow overflow range overrun 0x183D 6205 Flow Underflow Underrun 2 Warning flow underflow underflow underflow range range underflow range	run
0x183D 6205 Flow Underflow Underrun 2 Warning flow underflow range under the control of the cont	
0x183D 6205 Flow Underflow Underrun 2 Warning flow underflow range under	
range under	
1 1 1 1 1 1 1 1 1 1 1	
Ox183E 6206 Flow Cutoff Out Warning out of flow c	utoff
range	
0x183F 6207 Temperature MRE Overrun Warning temperature	
measuring ra	inge
overrun	
0x1840 6208 Temperature MRS Underrun Warning temperature	
measuring ra	inge
0x1841 6209 Temperature Overflow Overrun 2 Warning temperature	
0x1841 6209 Temperature Overflow Overrun 2 Warning temperature overflow rar	
overrun	ige
0x1842 6210 Temperature Underflow 2 Warning temperature	
Underrun 2 Warning temperature	
underrun	ilige
0x1843 6211 NVM Error 4 Error non-volatile	
memory is co	orrupt
0x1844 6212 Subslave Lost Error communicat	•
subslave	
interrupted	
0x1845 6213 Subslave Not Found 4 Error cummunicat	ion to
subslave cou	ldn`t
be astablished	ed
0x1846 6214 Emptypipe Warning no media in	tube
0x1847 6215 Temperature Sensor Error 4 Error no sensor att	tached
0x1848 6216 Measuring Circuit Saturated 2 Warning ADC out of ra	ange
0x1849 6217 Counter Overflow 2 Error volume or	
partvolume of	
overflowed	counter

page 60 MIM 01/0721

Event Code [hex]	Event Code [dec]	Name	Device Status	Туре	Definition
0x184A	6218	Dosing Timeout		Warning	indicades that the no flow timeout of the dosing function is active
0x184B	6219	Simulation Active		Warning	indicades that one of the simulations is running

17.3 IO-Link system command table

Command (hex)	Command (dec)	Command name
0x82	130	Restore factory settings
0xA0	160	Reset part volume counter
0xA1	161	Start flow simulation
0xA2	162	Stop flow simulation
0xA3	163	Start temperature simulation
0xA4	164	Stop temperature simulation
0xA5	165	Start part volume simulation
0xA6	166	Stop part volume simulation
0xA7	167	Events Handling ON
0xA8	168	Events Handling OFF
0xA9	169	Reset MinMax for Flow
0xAA	170	Reset MinMax for Temperature

17.4 IO Link ISDU parameter table

Parameters relating to the measured values flow, temperature or volume must be entered in the basic units and, if necessary, converted beforehand. The basic units are:

Flow: **L/min** Temperature: °C Volume: **liters**

Units conversion table

Category: FI	ow	
Unit	description	conversion
L/m	Liters per minute	-
	(basic unit)	
L/h	Liters per hour	1 L/h = 0.0167 L/m
mL/m	Milliliters per minute	1 mL/m = 0.001 L/m
m ³ /h	Cubic meters per hour	$1 \text{ m}^3/\text{h} = 16.667 \text{ L/m}$
gal/m	US gallons per minute	1 gal/m = 3.7854 L/m
gal/h	US gallons per hour	1 gal/h = 0.06309 L/m
galk/m	UK gallons per minute	1 galk/m = 4.54609 L/m
galk/h	UK gallons per hour	1 galk/h = 0.07577 L/m
L/s	Liters per second	1 L/s = 60 L/m
mL/s	Milliliters per second	1 mL/s = 0.0000167 L/m
USER	user unit	1 user unit = USER * L/m

Category: Temperature						
Unit	description	conversion				
°C	degree Celsius	-				
	(basic unit)					
°F	degree Fahrenheit	x °C = (32 + x *1,8) °F				
USER	user unit	1 user unit = USER * °C				

Category: Vo	Category: Volume						
Unit	description	conversion					
L	Liters	-					
	(basic unit)						
mL	Milliliters	1 mL = 0.001 L					
m^3	Cubik meters	$1 \text{ m}^3 = 1000 \text{ L}$					
galUS	US gallons	1 galUS = 3.7854 L					
galUK	UK gallons	1 galk = 4.54609 L					
barrel	Barrel (US)	1 barrel = 158.99 L					
USER	user unit	1 user unit = USER * L					

page 62 MIM 01/0721

Index [hex]	Name	Description	Factory default	Max Value	Min Value	Length [Bytes]	Data Type	Access
System								
0x0002	SystemCommand	See Table "Comand Codes"				1	UIntegerT	W
Product I	 dentification (Vendor	specific parameters)						
0x0010	VendorName		Kobold Messring			max. 20	StringT	R
0x0011	VendorText		www.kobold.com			max. 32	StringT	R
0x0012	ProductName		MIM- XXXXXXXXXXX			max. 16	StringT	R
0x0013	ProductID		[exact model code]			max. 16	StringT	R
0x0014	ProductText		magnetic inductive flow meter			max. 32	StringT	R
0x0015	Serialnumber	only read parameter				max. 8	StringT	R
0x0016	HardwareRevision					max. 8	StringT	R
0x0017	FirmwareRevision	Firmware Revision is constant in FW				max. 8	StringT	R
0x0018	ApplicationDevice Tag	tag name is from user configurable				32	StringT	R/W
0x0019	FunctionTag	function tag is from user configurable				32	StringT	R/W
0x0020	LocationTag	location tag is from user configurable				32	StringT	R/W

Index [hex]	Name	Description	Factory default	Max Value	Min Value	Length [Bytes]	Data Type	Access
Device Sta	atus Information				·			
0x0024	DeviceStatus	0 - Device OK 1 - Maintenance required 2 - Out of specification 3 - Functional check 4 - Failure				1	UIntegerT	R
0x0025	DetaildDevice Status					max. 20	ArrayT of OctetStringT 3	R
Display Co	onfiguration							
0x0100	DisplayOrientation	Orientation of display	1	(0) - Landsca (1) - Portrait (2) - Landsca (3) - Portrait	t Flip ape Flip	1	UIntegerT	R/W
0x0103	DisplayLayout	Single or dual layout	1	(0) - single (1) - dual		1	UIntegerT	R/W
0x0104	UpperDisplay	Source for the upper display	0	(0) - Flow (1) - Volume (2) - Temperature		1	UIntegerT	R/W
0x0105	LowerDisplay	Source for the lower display	2	(3) - Part Volume (0) - Flow (1) - Volume (2) - Temperature (3) - Part Volume		1	UIntegerT	R/W
0x0106	DisplayRefresh Time	Refresh intervall for the display [s]	0,5	10,0	0,5	4	FloatT	R/W
0x010A	LeftHotkey Function	Function for left hotkey	0	(0) - Off (1) - Value (2) - MinMa:	x	1	UIntegerT	R/W
0x010B	RightHotkey Function	Function for right hotkey	0	(0) - Off (1) - Value (2) - MinMa:	x	1	UIntegerT	R/W
0x010C	LeftHotkeySource	Source for the left hotkey	0	(0) - Flow (1) - Volume (2) - Temper (3) - Part Vo	rature	1	UIntegerT	R/W
0x010D	RightHotkeySource	Source for the right hotkey	0	(3) - Part Volume (0) - Flow (1) - Volume (2) - Temperature (3) - Part Volume		1	UIntegerT	R/W
0x010E	SensitivityOptical Keys	Sensitivity for the optical keys	0	(0) - low (1) - middle (2) - high		1	UIntegerT	R/W
0x010F	AutomaticMenu Leave	Automatic menu leaves if the timeout [s] is hit. 0 = timeout not active	0	60	0	1	UIntegerT	R/W

page 64 MIM 01/0721

Index [hex]	Name	Description	Factory default	Max Value	Min Value	Length [Bytes]	Data Type	Access
Output 1	In IO-Link mode outp	out 1 can be parameteri	zed individual, opera	ating mode ca	n only be chan	ged manual	ly)	
0x0110	OUT1Source	Source for the output (production setting)	0	(0) - Flow (1) - Volume (2) - Temperature (3) - Part Volume		1	UIntegerT	
0x0111	OUT1Type	Configuration of the output: 0-20mA, Pulse, Frequency (production setting)	8	(0) - disablec (1) - Alarm C (2) - 4-20mA (3) - 0-20mA (4) - 2-10V (5) - 0-10V (6) - Pulse O (7) - Frequer (8) - M12CO (9) - IO-Link (10) - Contro	output utput ncy Output M	1	UIntegerT	
0x0112	OUT1Alarm Function	Limit or window function for the alarm output	0	(0) - Limit (1) - Window		1	UIntegerT	R/W
0x0113	OUT1AlarmOutput Type	Alarm output NPN, PNP or Push pull	0	(0) - NPN (1) - PNP (2) - PushPull		1	UIntegerT	R/W
0x0114	OUT1AlarmSwitch Function	Alarm output normally opened or closed	0	(0) - normall (1) - normall		1	UIntegerT	R/W
0x0115	OUT1Alarm Threshold	Threshold for the alarm output [LPM/°C]	1,0	MRE	MRS	4	FloatT	R/W
0x0119	OUT1AlarmLower Threshold	Threshold for the alarm output used by the window function [LPM/°C]	1,0	OUT1Alarm Threshold	MRS	4	FloatT	R/W
0x011D	OUT1Alarm Hysteresis	Switching hysteresis for the alarm output [LPM/°C]	1,0	0	MBE - MBS	4	FloatT	R/W
0x0121	OUT1Alarm SuppressionFactor	How many times the threshold must be hit in order to switch the alarm output	0	60	0	1	UIntegerT	R/W
0x0122	OUT1Alarm Suppression Direction	for which direction the suppression factor is used	0	(0) - Up (1) - Down (2) - Both		1	UIntegerT	R/W

Index [hex]	Name	Description	Factory default	Max Value	Min Value	Length [Bytes]	Data Type	Access
0x0123	OUT1Analog NamurStandard	If enabled (1) the analog output conforms with the NAMUR Standard NE42. If disabled (0) the analog output stays in his equivalent range (e.g. 4-20mA)	1	(0) - NAMUF (1) - NAMUF		1	UIntegerT	R/W
0x0124	OUT1AnalogValue 0mA	The value from the slot used for the OmA scaling point [LPM/°C]	0,0	OUT1 Analog Value20mA	MRS	4	FloatT	R/W
0x0128	OUT1AnalogValue 4mA	The value from the slot used for the 4mA scaling point [LPM/°C]	0,0	OUT1 Analog Value20mA	MRS	4	FloatT	R/W
0x012C	OUT1AnalogValue 20mA	The value from the slot used for the 20mA scaling point [LPM/°C]	100,0	MRE	OUT1 Analog Value0mA	4	FloatT	R/W
0x0130	OUT1AnalogValue 0V	The value from the slot used for the 0V scaling point [LPM/°C]	0,0	OUT1 Analog Value10V	MRS	4	FloatT	R/W
0x0134	OUT1AnalogValue 2V	The value from the slot used for the 2V scaling point [LPM/°C]	0,0	OUT1 Analog Value10V	MRS	4	FloatT	R/W
0x0138	OUT1AnalogValue 10V	The value from the slot used for the 10V scaling point [LPM/°C]	100,0	MRE	OUT1Analog Value0V	4	FloatT	R/W
0x013C	OUT1PulseVolume	The volume represented by one pulse [L]	1,0	999,999	0,000001	4	FloatT	R/W
0x0140	OUT1PulseVolume Unit	Unit used for the pulse output	1	(0) - USER (1) - L (2) - mL (3) - m3 (4) - galUS (5) - galUK (6) - Barrel	1	1	UIntegerT	R/W
0x0141	OUT1PulseVolume UnitUser	User Unit used for the pulse output [L]	1,0	9999,9	0,0	4	FloatT	R/W
0x0145	OUT1PulseWidth	Width of each pulse [ms]	1	20000	1	2	UIntegerT	R/W

page 66 MIM 01/0721

1	UIntegerT UIntegerT	R/W
1	UIntegerT	
		R/W
4	FloatT	R/W
1 4 uency e0Hz	FloatT	R/W
1	UIntegerT	R/W
L		
1	UIntegerT	R/W
utput	UIntegerT	R/W
1	UIntegerT	R/W
1	UIntegerT	R/W
ned 1 ed	UIntegerT	R/W
4	FloatT	R/W
+	Floor	R/W
re	atput 1 ned 1 ed 4	1 UIntegerT 1 UIntegerT ned 1 UIntegerT

Index [hex]	Name	Description	Factory default	Max Value	Min Value	Length [Bytes]	Data Type	Access
0x0170	OUT2Alarm Hysteresis	Switching hysteresis for the alarm output [LPM/°C]	1,0	0	MBE - MBS	4	FloatT	R/W
0x0174	OUT2Alarm SuppressionFactor	How many times the threshold must be hit in order to switch the alarm output	0	60	0	1	UIntegerT	R/W
0x0175	OUT2Alarm Suppression Direction	for which direction the suppression factor is used	0	(0) - Up (1) - Down (2) - Both	I	1	UIntegerT	R/W
0x0176	OUT2Analog NamurStandard	If enabled (1) the analog output conforms with the NAMUR Standard NE42. If disabled (0) the analog output stays in his equivalent range (e.g. 4-20mA)	1	(0) - NAMUR disabled (1) - NAMUR enabled		1	UIntegerT	R/W
0x0177	OUT2AnalogValue 0mA	The value from the slot used for the OmA scaling point [LPM/°C]	0,0	OUT2 Analog Value20mA	MRS	4	FloatT	R/W
0x017B	OUT2AnalogValue 4mA	The value from the slot used for the 4mA scaling point [LPM/°C]	0,0	OUT2 Analog Value20mA	MRS	4	FloatT	R/W
0x017F	OUT2AnalogValue 20mA	The value from the slot used for the 20mA scaling point [LPM/°C]	100,0	MRE	OUT2Analog Value0mA	4	FloatT	R/W
0x0183	OUT2AnalogValue 0V	The value from the slot used for the 0V scaling point [LPM/°C]	0,0	OUT2 Analog Value10V	MRS	4	FloatT	R/W
0x0187	OUT2AnalogValue 2V	The value from the slot used for the 2V scaling point [LPM/°C]	0,0	OUT2 Analog Value10V	MRS	4	FloatT	R/W
0x018B	OUT2AnalogValue 10V	The value from the slot used for the 10V scaling point [LPM/°C]	100,0	MRE	OUT2Analog Value0V	4	FloatT	R/W

page 68 MIM 01/0721

Index [hex]	Name	Description	Factory default	Max Value	Min Value	Length [Bytes]	Data Type	Access
0x018F	OUT2PulseVolume	The volume represented by one pulse [L]	1,0	999,999	0,000001	4	FloatT	R/W
0x0193	OUT2PulseVolume Unit	Unit used for the pulse output	1	(0) - USER (1) - L (2) - mL (3) - m3 (4) - galUS (5) - galUK (6) - Barrel		1	UIntegerT	R/W
0x0194	OUT2PulseVolume UnitUser	User Unit used for the pulse output [L]	1,0	9999,9	0,0	4	FloatT	R/W
0x0198	OUT2PulseWidth	The width of each pulse [ms]	1	20000	1	2	UIntegerT	R/W
0x019A	OUT2Frequencyat FS	The max. frequency in Hz for the output [Hz]	500	1000	50	2	UIntegerT	R/W
0x019C	OUT2Frequency Overflow	The overflow frequency in percent of the max frequency [%]	1	100	0	1	UIntegerT	R/W
0x019D	OUT2Frequency Value0Hz	The value from the slot used for the OHz scaling point [Hz]	0,0	OUT2Frequ encyValue MaxHz	MRS	4	FloatT	R/W
0x01A1	OUT2Frequency ValueMaxHz	The value from the slot used for the max Hz scaling point [LPM/°C]	100,0	MRE	OUT2Freque ncyValue0Hz	4	FloatT	R/W
Dosing								<u> </u>
0x01B6	DosingValue	Dosing value [L]	0,0	9999,9	0,0	4	FloatT	R/W
0x01BA	DosingCorrection Value	Correction value which is added to the dosing value for the complete dosing counter [L]	0,0	Dosing Value	minus Dosing Value	4	FloatT	R/W
0x01BE	DosingUnit	Unit used for the dosing function	1	(0) - USER (1) - L (2) - mL (3) - m3 (4) - galUS (5) - galUK (6) - Barrel		1	UIntegerT	R/W

Index [hex]	Name	Description	Factory default	Max Value	Min Value	Length [Bytes]	Data Type	Access
0x01BF	DosingUnitUser	User Unit used for the dosing function [L]	1,0	9999,9	0,0	4	FloatT	R/W
0x01C3	DosingTimeout	Timeout in seconds for no flow [s]	0,5	10,0	0,5	4	FloatT	R/W
0x01C7	DosingCounter	Saved dosing volume counter stats	0,0	999999,0	-999999,0	4	FloatT	R
Service								
0x01CB	ServiceUser Password	Password for user service menu and main menu	0	99999	0	4	UIntegerT	R/W
0x01CF	ServiceUserMenu Locked	Whether main menu is locked or not	0	(0) - not lock (1) - locked	<u>l</u> xed	1	UIntegerT	R/W
0x01D0	SimulationAuto Stop	Auto stop for Simulation after time [min]	10	31	1	1	UIntegerT	R/W

page 70 MIM 01/0721

Index [hex]	Name	Description	Factory default	Max Value	Min Value	Length [Bytes]	Data Type	Access
Misc								
0x01D2	LanguageSelection	Language selection	0	(0) - English (1) - German (2) - French (3) - Spanish		1	UIntegerT	R/W
0x0262	OperatingHours Count	Operating hours counter [h]	0	429496729 6		4	UIntegerT	R
Flow				•	•		•	•
0x02F6	CutOff	Cut off for flow value [LPM]	0,0	MRE	0,0	4	FloatT	R/W
0x02FA	Unit	Unit used for flow	1	(0) - USER (1) - L/m (2) - mL/m (3) - L/h (4) - m3/h (5) - galUS/n (6) - galUS/h (7) - galUK/n (8) - galUK/h (9) - L/s (10) - mL/s	n	1	UIntegerT	R/W
0x02FB	UserUnit	User Unit used for flow [LPM]	1,0	9999,9	0,0	4	FloatT	R/W
0x0314	SimMode	Mode of the Simulation: Static, Triangle or Monotonic	0	(0) - Static (1) - Triangle (2) - Monotonic		1	UIntegerT	R/W
0x0315	SimStartValue	Value to start with the simulation [LPM]	0,0	9999,0	-9999,0	4	FloatT	R/W
0x0319	SimIncrement Value	Incrementation value of the simulation [LPM]	10,0	999,0	-999,0	4	FloatT	R/W
0x031D	SimNumber Intervals	Number of intervals to simulation	20	65000	1	2	UIntegerT	R/W
0x031F	SimTimingIntervals	Timinig in ms between intervals	50	50000	50	2	UIntegerT	R/W
0x0321	ValueInSiUnit	Saved flow value in SI unit [LPM]	0,0	999999,0	-999999,0	4	FloatT	R
0x0325	MinValueInSiUnit	Saved min flow value in SI unit [LPM]	0,0	999999,0	-999999,0	4	FloatT	R

Index [hex]	Name	Description	Factory default	Max Value	Min Value	Length [Bytes]	Data Type	Access
0x0329	MaxValueInSiUnit	Saved max flow value in SI unit [LPM]	0,0	999999,0	-999999,0	4	FloatT	R
Volume	<u> </u>							
0x0359	CountingType	counting type for a volume slot -> absolute or bidirectional	0	(0) - absolute (1) - bidirectional		1	UIntegerT	R/W
0x035E	Unit	Unit used for volume	1	(0) - USER (1) - L (2) - mL (3) - m3 (4) - galUS (5) - galUK (6) - Barrel		1	UIntegerT	R/W
0x035F	UserUnit	User Unit used for volume [L]	1,0	9999,9	0,0	4	FloatT	R/W
0x0385	ValueInSiUnit	Saved volume value in SI unit [L]	0,0	999999,0	-999999,0	4	FloatT	R
Temperat	ure							
0x03C2	Unit	Unit used for temperature	1	(0) - USER (1) - °C (2) - °F		1	UIntegerT	R/W
0x03C3	UserUnit	User Unit used for temperature [°C]	1,0	9999,9	0,0	4	FloatT	R/W
0x03DC	SimMode	Mode of the Simulation: Static, Triangle or Monotonic	0	(0) - Static (1) - Triangle (2) - Monotonic		1	UIntegerT	R/W
0x03DD	SimStartValue	Value to start with the simulation [°C]	0,0	9999,0	-9999,0	4	FloatT	R/W
0x03E1	SimIncrement Value	Incrementation value of the simulation [°C]	10,0	999,0	-999,0	4	FloatT	R/W
0x03E5	SimNumber Intervals	Number of intervals to simulation	20	65000	1	2	UIntegerT	R/W
0x03E7	SimTimingIntervals	Timinig [ms] between intervals	50	50000	50	2	UIntegerT	R/W

page 72 MIM 01/0721

Index [hex]	Name	Description	Factory default	Max Value	Min Value	Length [Bytes]	Data Type	Access
0x03E9	ValueInSiUnit	Saved temperature value in SI unit [°C]	0,0	999999,0	-999999,0	4	FloatT	R
0x03ED	MinValueInSiUnit	Saved min temperature value in SI unit [°C]	0,0	999999,0	-999999,0	4	FloatT	R
0x03F1	MaxValueInSiUnit	Saved max temperature value in SI unit [°C]	0,0	999999,0	-999999,0	4	FloatT	R
Part Volu	 ne							
0x0421	CountingType	counting type for a volume slot -> absolute or bidirectional	0	(0) - absolute (1) - bidirectional		1	UIntegerT	R/W
0x0426	Unit	Unit used for part volume	1	(0) - USER (1) - L (2) - mL (3) - m3 (4) - galUS (5) - galUK (6) - Barrel		1	UIntegerT	R/W
0x0427	UserUnit	User Unit used for part volume [L]	1,0	9999,9	0,0	4	FloatT	R/W
0x0440	SimMode	Mode of the Simulation: Static, Triangle or Monotonic	0	(0) - Static (1) - Triangle (2) - Monotonic		1	UIntegerT	R/W
0x0441	SimStartValue	Value to start with the simulation [L]	0,0	9999,0	-9999,0	4	FloatT	R/W
0x0445	SimIncrement Value	Incrementation value of the simulation [L]	10,0	999,0	-999,0	4	FloatT	R/W
0x0449	SimNumber Intervals	Number of intervals to simulation	20	65000	1	2	UIntegerT	R/W
0x044B	SimTimingIntervals	Timinig [ms] between intervals	50	50000	50	2	UIntegerT	R/W
0x044D	ValueInSiUnit	Saved part volume value in SI unit [L]	0,0	999999,0	-999999,0	4	FloatT	R

Legend
MRE Measuring Range End
MRS Measuring Range Start

18. Manufacturer's declaration



MANUFACTURER'S DECLARATION OF CONFORMITY



We:

Kobold Messring GmbH Nordring 22-24 65719 Hofheim Germany

declare under our own responsibility that the product(s):

MIM-1******* (IO-Link Device)

to which this declaration refers conform to:

IO-Link Interface and System Specification, V1.1,
 July 2013 (NOTE 1,2)

• IO Device Description, V1.1, August 2011

IO-Link Interface and System Specification, V1.0,
 January 2009 (NOTE 1)

• IO Device Description, V1.0.1, March 2010

The conformity tests are documented in the test report: IO-Link_Device_TestReport_MIM_190301.pdf

Issued at Hofheim, 01.03.2019

Harald Peters
General Manager

Manfred Wenzel

Proxy Holder

Reproduction and all distribution without written authorization prohibited

Kleby ppa. Wille

NOTE 1 Relevant Test specification is V1.1, July 2014

NOTE 2 Additional validity in Corrigendum Package 2015

page 74 MIM 01/0721

19. EU Declaration of Conformance

We, KOBOLD Messring GmbH, Hofheim-Ts, Germany, declare under our sole responsibility that the product:

Electromagnetic Flowmeter Model: MIM -1xxxxxxxxxx

to which this declaration relates is in conformity with the standards noted below:

EN 61326-1:2013

Electrical equipment for measurement, control and laboratory use – EMC requirements - Part 1: General requirements

EN 60529:2014

Degrees of protection provided by enclosures (IP Code)

DIN EN IEC 63000:2018

Technical documentation for the assessment of electrical and electronic products with respect to the restriction of hazardous substances

Also, the following EC guidelines are fulfilled:

2014/30/EU EMC Directive

2011/65/EU RoHS (category 9)

2015/863/EU Delegated Directive (RoHS III)

Additional for MIM-13xxx:

Regulation (EC) No 1935/2004 materials and articles intended to come into contact with food and repealing

Regulation (EC) No. 2023/2006 good manufacturing practice for materials and articles intended to come into contact with food)

Hofheim, 24 May 2021

H. Volz General Manager M. Wenzel Proxy Holder

ppa. Wully

20. UK Declaration of Conformity

We, KOBOLD Messring GmbH, Hofheim-Ts, Germany, declare under our sole responsibility that the product:

Electromagnetic Flowmeter Model: MIM -1xxxxxxxxxx

to which this declaration relates is in conformity with the standards noted below:

BS EN 61326-1:2013

Electrical equipment for measurement, control and laboratory use. EMC requirements. General requirements

BS EN 60529:1992+A2:2013

Degrees of protection provided by enclosures (IP-Code)

BS EN IEC 63000:2018

Technical documentation for the assessment of electrical and electronic products with respect to the restriction of hazardous substances.

Also, the following UK guidelines are fulfilled:

S.I. 2016/1091 Electromagnetic Compatibility Regulations 2016

S.I. 2012/3032 The Restriction of the Use of Certain Hazardous Substances

in Electrical and Electronic Equipment Regulations 2012

Additional for MIM-13xxx:

Regulation (EC) No 1935/2004 materials and articles intended to come into contact with food and repealing

Regulation (EC) No. 2023/2006 good manufacturing practice for materials and articles intended to come into contact with food)

Hofheim, 24 May 2021

H. Volz General Manager M. Wenzel Proxy Holder

ppa. Wully

page 76 MIM 01/0721