

#### **Product Features**

- High accuracy (±0.1%)
- 2-wire loop powered 4-20 mA output
- Linearized output to temperature
- Input RTD Pt100 with 3-wire compensation
- Analog design, potentiometer adjustable
- Factory calibrated for fixed range
- **DIN Rail-Mounted**

## **Description**

The RT810D Series analog 2-wire, or loop powered, temperature transmitters offer the most effective price/performance ratio in the industry. Factory calibrated for fixed range, they provide a 4-20 mA output linearized to temperature for Pt100. The wide temperature range and stocked availability make the RT810D an excellent choice for temperature signal transmission.

Precision 20-turn potentiometers allow fine adjustment of ZERO and SPAN. RT810D transmitters are of high quality, very accurate and feature completely linearized output to temperature. They are DIN rail-mounted conforming to DIN standard 46277 package which is very compact.

### **Specifications**

**@Vnom** = 24 VDC, **T.ambient** = 25°C, **Span nom.** = 100°C

Input: Pt100, 3-wire, α=0.00385, DIN EN 60751

Output : 4-20 mA loop powered, linear to temperature

Linearization ±0.01% FS

**Power Supply** 12-32 VDC, polarity protected

Supply Effect Zero Drift: ±0.01% FS/°C ±0.01% FS/℃ Span Drift: Long Term Drift: ±0.05% FS/year

**Excitation Current RTD:** 0.8 mA

Sensor Lead Resistance RTD: 500 ohm max.

Accuracy: 0.1 % FS (includes effects of linearity,

hysteresis and repeatability)

Span/Zero Adjustment : 20 turn potentiometer,

±10% for zero and span

Maximum Loop Resistance: Rmax. = [Vsupply - 9VDC] / 20 mA

Open Circuit Detection: Over-scale limit: 27.0 mA, Under-scale limit: 2.2 mA

Warmup: 30 seconds

Ambient Operating Temperature : -40°C.....80°C (-40°F....176°F) Storage Temperature: -40°C....80°C (-40°F....176°F)


DIN Rail: DIN 46277 **Housing Material:** Polyamide

**Housing Dimensions:** 2.44" W x 2.50" H x 0.71" D

- Information furnished by Intempco is believed to be accurate and reliable. However, no responsability is assumed by Intempco for its use.
- · Specifications subject to change without notice.



#### **Dimensions**



Temperature Standard Ranges		Input
°C	(°F)	Pt100 (P)
-50/+50	(-58/+122)	•
0/+50	(32/+122)	•
0/+100	(32/+212)	•
0/+200	(32/+392)	•
0/+300	(32/+572)	•
0/+400	(32/+752)	•
0/+600	(32/+1112)	•
0/+800	(32 /+1472)	•

For non-standard temperature ranges, specify range

# **Custom Builder**

I	Nodel	Input Code	Range
R	T810D	Р	(/)

Ex.: RT810D - P - (0/100°C)

www.intempco.com TX9.0 Rev. A-2010